
LOAD TESTS OF A THROUGH TRUSS BRIDGE BEFORE AND AFTER THE INSTALLATION OF. (U) AIR FORCE INST OF TECH WRIGHT-PATTERSON AFB OH R E HALLER AUG 83 AFIT/CI/NR-83-81T F/G 13/13 AD-A139 140 1/1 UNCLASSIFIED NL



Programme and Second Contract Contract

MICROCOPY RESOLUTION TEST CHART NATIONAL BUREAU OF STANDARDS - 1963 - A 16. DISTRIBUTION STATEMENT (of this Report)

APPROVED FOR PUBLIC RELEASE; DISTRIBUTION UNLIMITED

7. DISTRIBUTION STATEMENT (of the obstract entered in Block 20, if different from Report)

18. SUPPLEMENTARY NOTES

APPROVED FOR PUBLIC RELEASE: IAW AFR 190-17

10 Fullery

LYNN E. WOLAVER
Dean for Research and
Professional Development

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)

20. ABSTRACT (Continue on reverse side if necessery and identify by block number)

ATTACHED




DD 1 JAN 73 1473 EDITION OF 1 NO

**UNCLASS** 

84 03 19 101

8,8

I, Richard Eugene Haller, do grant permission for my thesis to be copied.



# LOAD TESTS OF A THROUGH TRUSS BRIDGE BEFORE AND AFTER THE INSTALLATION OF AN ARCH-SUPERPOSITION SCHEME

by

Richard Eugene Haller

A Thesis

Presented to the Faculty of Bucknell University in Partial Fulfillment of the Requirements for the Degree of Master of Science in Civil Engineering

Approved: Advisor

Department Chairperson

August 1983

TEXTSOCIAL TOTAL OF THE PROPERTY OF THE PROPER

# **ACKNOWLEDGEMENTS**

I am grateful to Dr. James G. Orbison, my advisor, for his guidance during this endeavor. I would like to thank all the people and organizations who made this project possible: Bucknell Small Business Development Center, Charles Hopta, Northumberland County Engineer, Dr. Jai B. Kim, Dr. Robert J. Brungraber, Williamsport Fabricators, George Waltman, Thomas Thul, Robert Murcek, Paul Paino, Vince Mehringer, Hendrick Kong, and the United States Air Force for providing the time to complete this thesis. Finally, a special thank you to my parents and all those who put up with me during the year.

# TABLE OF CONTENTS

	ACKNOWLEDGEMENTS	i.
	LIST OF TABLES	i
	LIST OF FIGURES	•
	ABSTRACT	vi:
1.	INTRODUCTION	
2.	INITIAL FIELD TEST	
	Description of the Bridge	
	Test Equipment and Theory	
	Test Procedure	10
	Test Results	13
	Analytical Results	14
	Other Tests Conducted	19
	Discussion	2
	Chapter Summary	20
3.	FINAL FIELD TEST	2
•	Description of Arch-Superposition	
	Scheme	2
	Test Theory	30
	Test Procedure	3
	Test Results	3:
	Analytical Results	3:
	Other Tests Conducted	3!
	Discussion	3'
	Chapter Summary	4
4.	COMPARISON OF INITIAL AND FINAL TEST	
	RESULTS	40
5.	SUMMARY AND DISCUSSION	5
6.	CONCLUSIONS	56
7.	BIBLIOGRAPHY	51
8.	APPENDICES	58
	Appendix 1 Bridge Rating	
	Calculations	59
	Appendix 2 Sample Computer Output	65

# LIST OF TABLES

1	Initial Test Experimental and Theoretical Truss Member Stresses (ksi) - Upstream Truss	15
2	Initial Test Experimental and Theoretical Truss Member Stresses (ksi) - Downstream Truss	16
3	Initial Test Experimental and Theoretical Truss Vertical Deflections (inches)	17
4	Final Test Experimental and Theoretical Arch Section Stresses (ksi) - Upstream Truss	33
5	Final Test Experimental and Theoretical Arch Section Stresses (ksi) - Downstream-Truss	34
6	Deflection Results from the Second Bridge to Have the Arch-Superposition Scheme Installed (inches)	38
7	Final Test Experimental and Theoretical Truss Member Stresses (ksi) - Upstream Truss	41
8	Final Test Experimental and Theoretical  \ Truss Member Stresses (ksi) - Downstream Truss	42
9	Final Test Experimental and Theoretical Truss-Arch Deflections (inches).	43
10	Percent Reduction in Truss Live Load Member Stresses - Upstream Truss	47
11	Percent Reduction in Truss Live Load  Member Stresses - Downstream  Truss	48
12	Percent Reduction in Truss Deflections	50

# LIST OF FIGURES

1	Truss Dimensions and Member Cross Sections Northumberland County Bridge	
	Number 50	4
2	Northumberland County Bridge Number 50	6
3	Damaged Truss Members	
	(a) Member Number 14 - Upstream	- 7
	Truss(b) Member Number 18 - Down-	•
	stream Truss	٤
4	Strain and Dial Gauge Locations	10
5	Set Up of the Dial Gauges for Deflection	
	Measurement	11
6	Test Vehicle Loading Positions	12
7	Test Vehicle and Wheel Weights	13
8	Downstream Truss with the Truss-Arch	
	Scheme Installed	28
9	Strengthening of the Timber Deck	
	(a) Existing Deck System	28
	<ul><li>(b) Additional Steel Stringers</li><li>Added to Shorten the Deck</li></ul>	
	Span Length	29
_	Wombon Designations for large Costions	21
.0	Number Designations for Arch Sections	31
1	Loaded Hanger Rods - Typical for Load	
	Positions One Through Four	35
.2	Looking Upstream at a Second Bridge to	
	Have the Arch-Superposition	
	Scheme Installed. Coudersport,	
	Potter County, Pennsylvania	39
.3	Arch End Support - Steel Plates on	
	Neoprene Pads	39
4	Stiffening of the Top Chord to Increase	
	Bridge Capacity	54
. 5	Prestressing of the Lower Chord to	
	Increase Bridge Capacity	54

16	Shifting	of	the	End	Supports	to	Increase	
		Bi	idge	Cap	pacity			55

#### ABSTRACT

Because so many pinned and riveted truss bridges currently are classified as structurally deficient, a need to develop an economical, practical alternative to bridge replacement exists. Rehabilitation by an arch-superposition scheme can effectively reduce truss member stresses and increase the bridge load capacity. This was verified by load tests conducted both before and after the installation of the arch-superposition scheme to Northumberland County bridge number 50. The results showed that truss member stresses and deflections can be reduced at least 50% by the scheme which is approximately one-seventh the cost of bridge replacement. Bridge number 50 has been upgraded from a six to a 20 ton inventory rating. The theory, economics, and construction feasibility of the arch-superposition scheme have been verified.

### 1. INTRODUCTION

Numerous articles have been published recently on the dire condition of the country's bridges. There are 568,000 federally and state owned roadway bridges in this country, of which 72% where built prior to 1935. Also, 373,000 bridges are owned by county and local governments, 92% of which were built prior to 1935. Based upon results from the federal bridge inspection program completed in 1981, 106,923 of the state bridges (both on and off the federal aid system) been classified have as deficient -- unable to carry today's heavy truck loads. It is estimated that \$41.1 billion is needed to rehabilitate or replace these bridges. Clearly, spending this much money is, at present, politically unacceptable. Thus, alternative structurally economically viable methods and rehabilitation must be developed. Due to continuing decay, the number of deficient bridges will increase each year unless appropriate measures are taken [1].

Many of the structurally deficient bridges are pinned or riveted truss bridges, a common design prior to 1935. Where applicable, truss type bridges can be rehabilitated by utilizing an arch-superposition scheme. This scheme would increase the load carrying capacity of the

<sup>[1]</sup> Numbers in brackets refer to references listed in the bibliography at the end of the thesis.

bridge to at least 20 tons with minimal traffic interruption since the bridge need not be closed to complete the work.

The bridge rehabilitation is completed by superingosing steel arches upon each truss and adding floor beams between existing ones [2]. In this manner, bridge loads can be increased and the threat of sudden failure, a major concern for truss bridges, is greatly reduced.

This thesis addresses the actual effectiveness of the scheme. Measurements of arch-superposition deflections and member stresses were taken during the load testing of an actual bridge both before and after installation of the arch-superposition scheme. Further, a comparison of experimental and theoretical stresses presented to determine differences between the design (ideal) and actual trusses, the reasons for these differences and the ability of a computer program to accurately model the structure.


The body of this thesis is broken into three sections. The first section describes the initial test conducted prior to the arch installation, the second section describes the test conducted after the bridge rehabilitation was completed, and the final section presents a comparison of test results from the first two sections.

#### 2. INITIAL FIELD TEST

## The Test Bridge

The test bridge, Northumberland County bridge number 50, spans Roaring Creek, located in central Pennsylvania between Northumberland and Columbia Counties. The region surrounding the bridge is principally occupied by camping areas and summer homes. Due to the bridge's five-ton weight limit, large campers, fuel oil delivery trucks, and snow removal and firefighting equipment are forced to detour the bridge.

Bridge number 50, built in 1895, is a five-panel through truss with a total length of 72'-11" and height of 16'-0". The deck is made up of two by four inch (nominal) timber planks (on edge) supported by six by twelve inch (full) timber stringers. The floor beams, which are twelve inch deep Wide Flange sections, are rated at eight-tons operating and six-tons inventory. An operating rating is the maximum allowable live load that can be safely supported by the bridge. An inventory rating is the maximum live load that can be applied to the bridge an infinite number of times without affecting its strength. The floor beams control the allowable bridge load capacity (see Appendix 1). Figures 1 and 2 contain sketches and photographs of the bridge and member cross sections. Both of the bridge



ACCOUNT TO STATE OF THE STATE O

Member	Description	Cross Section
6,7,9,10	Lower Chord Tension Eye Bars	1 ½" x 2"
8	Same as 6,7,9,10	3/4" x 2"
1-5	Top Chord - Composed of 2 Channels and Cover Plate	10"
11,14	First and last Verticals	☑ 15/16" sq.
12,13	Interior Verticals	10"
15,18	Diagonals	2 ½" x 2"
16,17	Counters	2 2 1" sq.
19	Floor Beams	12"

Figure 1: Truss Dimensions and Member Cross Sections.
Northumberland County Bridge Number 50.

abutements are constructed of masonry with the near abutment (Northumberland County side) also having a concrete jacket.

The damage to several of the truss members affects their load carrying capacities. On the upstream truss the first vertical member (number 14 in Figure 1) made up of two 15/16 inch square bars is bent about twenty degrees from the vertical, two feet from the lower chord pin (see Figure 3). This damage appears to be from debris impact during a period of high water.

On the downstream truss, the second interior vertical member (number 12) made up of two channel sections joined by lacing bars is damaged from an auto collision with the bridge railing near the member. The inside channel section is bent outward and the lacing bars are buckled. The inside, near diagonal, a one-half by two inch rectangular bar is very loose and would appear not to carry any load (see Figure 3). The near-end post composed of a cover plate riveted to two channels, has rotated outwards from auto impact. This rotation in turn bent the first outside eyebar of the lower chord. The outside, lower chord eyebar of the center panel is bent upward possibly from debris impact during high water.

Additionally, four timber stringers are severely deteriorated although three of the four are outside stringers. The top flange of all four floor beams have section losses of up to 50% due to heavy corrosion. At some





ACCOUNTS OF THE CONTROL OF THE STATES OF THE

Looking from Northumberland to Columbia Counties.
Upstream truss to the right.

Figure 2: Northumberland County Bridge Number 50



Figure 3(a): Damaged truss members, member number 14 - upstream truss



Figure 3(b): Damaged truss members, member number 18 - downstream truss


time a one-quarter inch plate was welded to the top flange of the floor beams providing additional area.

Because of the eight-ton operating rating, the low underclearance allowing easy access, and the relatively low average daily traffic count, the bridge is an ideal choice for application of both the arch-superposition scheme and load testing.

# Test Equipment and Theory

To record member strains, electrical resistance strain gauges were used along with a digital strain recorder. The strain gauges were attached to a select number of members whose surfaces were first sandblasted and ground to form a smooth, clean surface. Pigtails, or short lead wires, were soldered to each gauge prior to covering the gauge and tabs with a waterproofing solution and putty.

A preliminary computer analysis of one of the trusses indicated the vertical, diagonal, and lower chord members to be the most highly stressed members. In order to obtain a complete picture of the stress distribution, gauges were attached to these members along with the end posts, interior vertical members, and counters on both the upstream and downstream trusses. In addition, two gauges were attached to each U-bolt, one on each side of the U, to determine the exact loads applied to each truss. Knowing these loads, one is able to determine any possible load distribution to adjacent floor beams by the deck system (see Figure 4 for a



X=strain gauge location O=deflection dial gauge location

Figure 4: Strain and dial gauge locations

gauge layout sketch). Since the members selected for study are subjected to axial loads only, the gauges were not always placed along the member centerline. Instead, they were placed at a location requiring the least amount of grinding and hence the least section loss.

#### Test Procedure

To load test the bridge, the following procedure was followed:

- (1) Connect the lead wires to the gauges and the digital strain recorder
- (2) Set up the dial gauges as shown in Figure 5 at each of the interior verticals
- (3) Calibrate and balance the recorder
- (4) Record the zero readings for both the strain gauges and deflection dials
- (5a) Move the test vehicle (H loading) to positions one through four, placing the truck rear wheels directly over each floor beam and straddling the roadway centerline (see Figure 6)

- (5b) At each loading position, record the gauge and dial readings
- (6) Repeat steps 3 through 5 at least twice more to verify reading consistency.

NOTE: For the first trial only, mark the exact wheel positions in order to locate the truck in the same position for all trials conducted and the final load test.

次の 「他のでは、 「しる。 「しる。 「しる。 「し。 「し。 「し。 「し。 「し。 



Figure 5: Set up of the dial gauges for deflection measurement. A thin wire from the dial to the weight in the water measures movement relative to the stream bed.





Figure 6: Test vehicle loading positions

# Test Results

The bridge was load tested on a sunny, warm (72 F) day. The quasi-static live load was applied by a Northumberland County gravel truck (see Figure 7). For load cases one through four, the rear wheels of the truck were placed directly over the floor beam and symmetrically about the

CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR CONTRACTOR

bridge centerline. Of a total of 76 gauges, readings were obtained from 54 gauges located on the trusses and eight gauges located on the U-bolts. Because of the steep creek bank, dial gauges were set up at only three of the four interior vertical members. Of these three gauges, one was defective giving erratic results.



Truck wheel weights and axle spacing



Two-axle gravel truck used to apply the live load Figure 7: Test vehicle and wheel weights

Tables 1 and 2 display the experimental, live load member stresses in kips per square inch (ksi) for loading positions one through four. These values were derived by first subtracting the initial zero reading from the readings for positions one through four for all three trials. Gauge strain readings are the average of the readings for the three trials. Since strain is directly proportional to stress, these strain readings multiplied by the modulus of elasticity (E) give average member stresses. For steel produced prior to 1905, the modulus of elasticity as given by the Manual for Maintenance Inspection of Bridges is 29,000 ksi [3]. A comparison of the three trial readings for each member gauge showed good consistency between each of the trials for most of the gauges.

Table 3 lists the truss live load deflections in inches for the dial gauges located on the interior vertical members as shown in Figure 4. Like the member stresses, truss deflections were determined by averaging the difference between the zero reading and the readings for positions one through four for all three trials.

## Analytical Results

Tables 1 through 3 also list the predicted member stresses and truss deflections. These values were calculated with the computer package PFENNIGS developed by Vince Mehringer of Bucknell University. Within PFENNIGS, member stresses and truss deflections are calculated by the

でしたこれでのの 選手 アンマンド は 半層で とびない アドル州 一直によったのない 対対

Table 1: Initial test experimental and theoretical truss member stresses (ksi) - upstream truss

Member 1			Loading Position 2 3				4	
Number	_	_					Act	-
1	-1.54	-1.57	-1.22	-1.16	84	73	35	31
5	38	54	-1.16	97	-1.86	-1.39	-1.16	-1.22
6	75	29	26	.60	.99	1.72	1.74	. 53
7	1.60	29	2.96	.60	2.99	1.72	67	.53
8	.73	1.14	1.91	2.27	1.65	1.83	.55	.50
9	2.20	2.27	.64	1.06	61	.07	96	38
10	1.94	2.27	.55	1.06	38	.07	64	38
11	4.55	4.50	.00	.00	•00	.00	.00	.00
12	.44	.46	. 29-	. 29	78	66	29	26
13	52	48	44	36	. 58	.61	.20	.27
14	•00	•00	.00	•00	. 78	1.76	2.81	4.50
15	•00	.17	4.32	4.03	2.93	2.55	1.28	1.07
16	-2.61	-1.85	-1.74	-1.13	3.19	2.67	1.36	1.07
17	1.65	1.94	1.45	1.47	-1.83	-2.43	-1.16	-1.07
18	.38	1.89	.15	3.39	1.02	2.78	1.42	-1.07

Act = Actual or experimental value Pred = Predicted or theoretical value

Note: For member number designations see Figure 1. Predicted values based upon computer run for pin-60% pin support conditions.


Table 2: Initial test experimental and theoretical truss member stresses (ksi) - downstream truss

Member	1			ading E		on B	4	1
Number	_	Pred	_	='	Act	Pred	Act	Pred
1	75	-1.57	58	-1.15	44	73	15	31
5	49	54	78	96	-1.10	-1.38	99	-1.22
. 6	70	.02	12	.92	.87	2.04	1.42	2.11
7	1.80	.02	3.48	.92	3.22	2.04	81	2.11
8	49	.99	1.77	2.26	2.61	1.61	49	. 45
9	.35	2.58	09	1.39	.20	.42	.64	17
10	3.05	2.58	2.09	1.39	1.10	.42	.12	17
11	3.42	4.50	.00	•00	06	.00	.00	.00
12	4.06	.10	.58	.08	-1.07	-1.13	-2.70	48
13	38	83	29	60	.15	.15	.15	.06
14	.15	• 00	.20	•00	1.54	1.70	4.50	4.51
15	.00	.14	•00	4.01	3.45	2.55	1.10	1.07
16	.09	38	20	24	2.41	4.56	. 96	1.92
17	1.74	3.37	1.25	2.41	87	51	58	23
18	73	1.88	09	3.36	.75	2.80	1.13	-1.07

Act = Actual or Experimental Value Pred = Predicted or Theoretical Value

Note: For member number designations see Figure 1. Predicted values based upon computer run for pin-50% pin support conditions.

Table 3: Initial test experimental and theoretical truss vertical deflections (inches)



	1	Loading 2	Position 3	4
Gauge	Act Pred	Act Pred	Act Pred	Act Pred
1	.030 .043	.086 .090	.100 .099	.037 .035
2	.032 .038	.200 .089	.227 .113	.138 .042

Note: Upstream truss deflections computed with pin-60% pinned support condition, downstream truss with pin-50% pinned support condition. Positive deflection downwards.

plane frame program developed by Weaver and Gere. This program is based upon the stiffness method of analysis assuming structure linearity and elastic member properties.

Initial data inputs were based upon the results of a thorough inspection of the bridge. At both supports movement in the horizontal and vertical directions was prevented to model the pin supports. The cross sectional area of all the lower chord members was reduced by ten percent to account for corrosion of the steel. The pins along the lower chord were fixed against rotation in an

attempt to model the action of these corroded joints. Finally, to prevent the program from assigning a bending moment to a pin-connected member or a compressive force to a slender member, the moment of inertia or cross sectional area for the member was reduced to nearly zero. This reduction was done after an inspection of the member stresses calculated initially. Any slender member assigned a compressive load or bending moment had its cross sectional area or moment of inertia reduced in subsequent analyses.

A comparison of the actual and predicted stress results revealed a need for a better correlation. By modeling the truss twice, once with pin supports and once with a pin and support, predicted member stresses and truss deflections can be determined for the range between 0% and 100% pinned for the second support. Another comparison between the actual member stresses and the range of predicted stresses indicates many of the actual values now within the predicted range achieving a better fall correlation. However, the effect of the damaged and loose members has not been modeled. In addition, the behavior of the lower chord pinned joints has only been estimated by fixing the joints against rotation in an attempt to model their high friction. These shortcomings in the computer model of the truss are the principal reasons for the deviations of some actual member stresses from the range of predicted values.

As with the member stresses, the upstream truss actual deflections correspond well with the predicted values. The downstream truss actual deflections are higher than the predicted deflections for load positions two, three and four. This is principally due to the looseness of the joints which allows a certain amount of deflection prior to load application to the truss members.

### Other Tests Conducted

Many bridges have been load tested over time by various methods in an effort to determine actual stresses and deflections. These actual values can then be used to evaluate current methods of analysis and design, particularily the AASHTO specifications for the design and rating of all types of bridges. With this in mind, several through truss bridges have been tested.

One series of tests was conducted by the Engineering Research Institute at Iowa State University [5]. The objective of the tests was to compare the 1975 AASHTO bridge design and rating procedure with the observed field behavior of pin-connected, high truss bridges. A total of four spans from two separate bridges were tested. One span from a Parker truss bridge was tested to its ultimate load capacity while a second and third span and a span from a modified Pratt truss bridge were tested under service loads. Recorded member forces and truss deflections were compared with theoretical forces computed assuming all members were

joined by ideal pins. For the ultimate load test, most strain readings agreed closely with the theoretical forces calculated. However, the load-deflection curves for the lower chord pins differed considerably in magnitude from the theoretical curves. This behavior was attributed to "the frozen condition of the truss joints resulting from the rusted members and pins "[5, p. 26]. From the ultimate load test results it was concluded that "although the actual conditions in the joints are unknown, considering the truss to be pin-connected does provide a realistic method of truss analysis" [5, p. 26].

For the service load tests, the procedure followed was very similar to that followed in the testing of Northumberland County bridge number 50. Theoretical member influence lines and truss deflection values were developed be a determinate method of analysis. When compared with these theoretical values the experimental results were consistently lower. This difference was due to the partial deck continuity (not accounted for in the analysis), the condition of the joints and problems in the instrumentation. Therefore, it was concluded that "the analysis of a pin-connected truss, even though the condition of the pins is unknown, as a simple determinate truss will provide a conservative indication of the bar forces and truss deflections" [5, p. 32].

A second series of tests was conducted by C. P. Heins

involving the load testing of six truss bridges and the evaluation of the AASHTO stringer load distribution factor [6]. Both static and dynamic tests were conducted to determine the effect of wooden nailing strips attached to each stringer upon the bridge capacity. Total member stresses were found by adding the field determined live load stresses to the computed dead load stresses. These total stresses when compared with the analytical total member stresses were consistently smaller in magnitude. It was concluded that determinate analytical methods used are too conservative in their estimate of bridge capacities.

## Discussion

As previously mentioned, the truss supports of Northumberland County bridge number 50 act somewhere between an ideal pin and-roller support. A careful comparison of the actual stresses and the range of predicted values indicates a best fit at 50% pinned for the downstream truss and 60% pinned for the upstream truss. The predicted values in Tables 1 through 3 are determined with pin-50% pin or pin-60% pin end supports for the downstream and upstream trusses respectively.

The member stresses for a truss with pin-50% pin or pin-60% pin end supports are calculated by multiplying both the pin-pin and pin-roller stresses by 0.5 and 0.5 or 0.6 and 0.4 respectively and adding them together. The 50 and 60% figures are an average of the percent values for each

member of the upstream or downstream trusses. (An average for each of the four load positions was determined first. The final truss support conditions are an average of these four averages.) The member percent value represents the end support conditions at which the predicted stress (calculated with the computer model) exactly equals the experimental member stress.

The upstream and downstream trusses acted differently. Not only were the end support conditions different, but also the stresses in the counters. To improve the correlation between theoretical and experimental values, the cross sectional area of the downstream counters was reduced to one-tenth of a square inch while the upstream counters were maintained at one square inch. This correction in area was required since the compression in the slender members varied between the two trusses.

Since there is only one significantly damaged member in the upstream truss versus five in the downstream truss, the member stresses and truss deflections correlate better with the predicted values. For all four load cases most of the stresses in the upstream truss lower chord and vertical members correspond well. However, some deviation in the diagonals and counters is present. There would appear to be two additional causes for this deviation. First, the panel length of 14'7" is slightly longer than the truck length of 14'0". Therefore, the floor beams located near the truck

front axle are loaded "eccentrically". This eccentric loading is evident from the U-bolt readings which read tension on one side and zero or even compression on the other. Also this was sometimes evident on the rear axle floor beams. From the "frozen" condition of the pins, a load distribution different from an ideal pin then occurs.

The second cause for the deviation in the diagonals and counters is the differences in member tightness or length. A tight member will begin carrying load immediately, while a loose member will carry load only after a sufficient deflection occurs at the lower chord pin.

The one damaged vertical member of the upstream truss (member 14) exhibited a stress considerably lower than predicted for load cases three and four. This lower stress would suggest a redistribution of member forces to adjacent members has occurred.

The experimental member stresses and truss deflections of the downstream truss vary from their predicted values more than do those of the upstream truss due to the five significantly damaged members previously mentioned. For example, the loose diagonal, one of two composing member 8 of the downstream truss, results in considerably lower stresses than predicted for load cases one through three. In general, the members close to the load application points had stress values that varied considerably from the predicted stresses indicating a transfer of loading to the

で対面内ではなるなどで、「「ないない」とは、

truss by the U-bolts and pins other than that predicted. This variation is particularly true for load cases one and four.

A comparison of the upstream and downstream deflections in Table 3 shows the downstream truss deflecting approximately twice as much as the upstream truss for load cases two through four. Further, the actual upstream truss deflections compare very closely with the predicted deflections. The downstream deflections do not. Similarly, good correlation existed for the upstream truss member stresses but not for the downstream truss member stresses.

Based upon the test results obtained, a typical pin-connected truss can be analyzed with the aide of a computer model utilizing the stiffness method of analysis which assumes structure linearity and elastic member properties. However, the accuracy of the analysis depends upon the accuracy of the input data obtained from a thorough bridge inspection. To ensure that the maximum member stresses are obtained, the counter cross-sectional area should be reduced as required (depending upon the load position) to prevent compressive loading of a slender member. Also the truss should be analyzed with both pin-pin and pin-roller end supports despite the type of supports that exist in the field. Although the majority of members are most highly stressed in the pin-roller condition, some most highly stressed in the pin-pin condition, are

principally the interior verticals and counters. Finally, all possible load positions should be investigated.

It should be stressed that the analysis assumes uniform member properties along the entire length. Therefore, the minimum section properties are considered uniform along the member length. This minimum section will often occur near connections and in areas subject to roadway splash. Because of limited access to many connections, their condition is often the most difficult to evaluate.

Sanders et al. [5] and Heins [6] determined that analyzing a truss bridge as pin connected and determinate is a realistic way of establishing the ultimate and service load capacities of a truss bridge provided the partial deck continuity is accounted for. The test of bridge number 50 verified this conclusion provided that careful consideration of the analysis input data be given.

シャン・ こうしょういい かいきょうしゅん みかん 自 はない とうじゅんき

4日かいのうないということになっているとは、

# Chapter Summary

There are four major kinds of structural imperfections possible in truss bridges:

- (1) Geometric imperfections
- (2) Imperfections in the loading system
- (3) Imperfections in the support conditions
- (4) Material imperfections

An inspection of the test bridge revealed that geometric imperfections exist in numerous damaged members with the majority being in the downstream truss. The test data revealed that imperfections in the loading system and support conditions also exist. The best fit theoretical data was calculated with pin-60% pin and pin-50% pin end support conditions for the upstream and downstream trusses respectively. The U-bolt readings revealed an "eccentric" loading of the floor beams since one side of the U-bolt carried most of the front and sometimes rear wheel loading.

The initial test proves that simple analyses of a truss will provide reasonable member stress values provided care is taken to model the existing truss conditions. Further, when maximum member stresses are required, the truss should be analyzed with both pin-pin and pin-roller end support conditions, all load positions, and reduced counter cross-sectional areas as required.

### 3. FINAL FIELD TEST

Description of Arch-Superposition Scheme

rehabilitation of Northumberland County bridge number 50 required the addition of steel arches, hanger rods, stringers, floor beams and the replacement of the four existing floor beams. A steel arch, made up of ten line segments having the same channel section but varying length, was placed just to the outside and inside of both the upstream and downstream trusses (see Figure 8). Additional hanger rods and floor beams were placed between the existing vertical members and floor beams, halving the stringer span length and improving the arch efficiency by increasing the number of loading points. The reduced span length of the stringers increased their load capacities to twenty tons (H20-44), eliminating the need for replacement. However, the two by four inch timber decking was not sufficient to carry an H20-44 loading. There were two possible options: first, to replace the existing timber deck (requiring the closing of the bridge), and second, to place additional stringers between the existing wood stringers shortening the deck span length. Since the addition of steel stringers was lower in cost and required no disruption of traffic, it was the alternative selected (see Figure 9). For the design of the steel stringers, care was taken to match the member stiffness closely to the timber stringer

■ こうけんこと Manager ■ アンドンスを受けたためのと、■ アンドスを含む ■ 1900 にじょう Manager ■ 1900 によっている Manager



Figure 8: Downstream truss with the truss-arch scheme installed. New members have primer paint.



Figure 9(a): Strengthening of the timber deck. Existing deck system.



Figure 9(b): Strengthening of the timber deck.
Additional steel stringers added to shorten the deck span length.

stiffness.

With up to 50% section loss on the top flange and only an eight-ton capacity, all four of the existing floor beams were replaced. Finally, to withstand the horizontal thrust from the arch, the far abutment (Columbia County) required the addition of a nine-inch concrete jacket or skirt. As already mentioned, the near abutment was jacketed previously after a period of high water. For details on the design and construction schedule of this project see reference number 9.

The advantages of the arch-superposition scheme are as follows.

- (1) The bridge load carrying capacity can be increased to twenty tons (H20-44) by the addition of steel arches, hanger rods, floor beams and stringers.
- (2) The rehabilitation will not require complete closure of the bridge, only short delays.
- (3) Considerable cost savings can be achieved by eliminating the need to replace the bridge, particularily at today's design standards.
- (4) Redundancy is added to the bridge which will reduce the likelihood of collapse should a truss member or pin fail.

It is predicted that the trusses and arches of the bridge will act together to carry the applied loadings effectively. The percent of the total load carried by the trusses or arches will vary depending upon the load location. When the truck rear and front wheels are located near one of the added floor beams, most of the load will be carried by the arches. For a load location near "existing" floor beams, a greater load sharing between the trusses and arches will occur. In any load position the trusses provide lateral stability to the arches.

# Test Theory

To determine the validity of the truss-arch computer model used for the arch design, strain gauges were placed at the midlength of the first, second, sixth, ninth and tenth straight line segments on all four arches (see Figure 10).

Two gauges were placed at each midlength, approximately four and one-half inches above and below the channel's centroidal axis. One gauge was also placed on each hanger rod to determine the load distribution from the deck to the trusses and arches. Finally, the gauges from the initial load test were used to measure the percent reduction in truss member stresses.




Figure 10: Number Designations for Arch Sections

### Test Procedure

The same test procedure employed for the initial load test was used for the final load test. However, since there were now 130 strain gauges on the bridge, each trial was run twice due to the limited number of instrument channels available. The same four load positions from the initial test were used and care was taken to insure exact load placement for each of the three trial and two test runs. Because of the two test runs, deflection data was collected for a total of six trials, three trials from each test run.

#### Test Results

Tables 4 and 5 list the actual results from the arch gauges. These stresses are the product of the member strains (average of the three trials) and the modulus of elasticity. They represent the combined axial and bending stresses at points away from the channel centroidal axis. The existence of the bending moment results in a difference between the two stresses at each cross section. The highest arch member stresses monitored occur in the end sections nearest the loaded hanger rods. Of a total number of 40 gauges attached to both arches, only 27 were operational during the test.

## Analytical Results

Examination of the hanger rod stresses showed the truck loadings to be distributed to five floor beams and hanger rods (see Figure 11). The percent of the total weight distributed to each floor beam varied for each test The percent of the total truck weight distributed to each hanger rod was 9, 44, 21, 22, and 4% for load position one, 7, 66, 12, 11, and 4% for load position two, and 11, 54, 19, 12, and 4% for load position three. Only three hanger rods are loaded for load position four. The percent values are an average of the upstream and downstream hanger rod readings. In determining the predicted member stresses listed in Tables 4 and 5, the load distribution as determined from the field test was entered into the computer model. This load

Table 4: Final test experimental and theoretical arch section stresses (ksi) - upstream truss

3 m mb			1	Lo	oading	Positi	on		4
Arch Secti	on c	Act			t Pred	Act	Pred	Act	•
1-1	4.000	44	87	29	49	38	62	20	69
1-1	-4.125	90	-2.01	-1.16	58	84	44	46	73
1-0	4.250	58	83	32	49	35	62	15	69
1-0	-3.875	87	-1.97	-1.25	58	96	44	58	73
2~J	4.062	75	-3.53	06	. 22	06	.50	12	.55
2-I	-3.312	~.35	.47	-1.22	-1.16	99	-1.38	49	-1.75
2-0	4.437	-1.02	-3.74	~.15	. 29	09	.60	09	.67
2-0	-4.312	26	1.02	-1.65	-1.35	-1.48	-1.64	78	-2.07
6-I	4.250	52	-2.10	99	-1.65	73	74	. 26	2.13
6-I	-4.187								
6-0	4.125	44	-2.06	90	-1.61	64	73	.26	2.05
6-0	-4.062								
9-I	4.000	44	.65	~.55	.44	44	65	96	-4.48
9-I	-4.250								
9-0	4.125	58	.69	70	.47	52	65	-1.65	-4.58
9-0	-4.063			•					
10-1	4.125	49	80	49	61	29	61	12	65
10-1	-4.250	75	71	-1.16	44	-1.28	89	78	-2.00
10-0	4.125								
10-0	-4.312	93	71	-1.33	43	-1.31	89	58	-2.01

Note: For member number designations see Figure 1. Predicted values based upon computer run for 40% fixed-40% fixed arch support conditions.

Table 5: Final test experimental and theoretical arch section stresses (ksi) - downstream truss

N m = ln			1	Lo	_	Positi	_		
Arch	on c	N -4	_ D==3	8-4	2	No.	3 Drod	201	4 Drod
Secti	on e	ACT	rea	ACT	Pred	AC	Pred	AC	Pred
1-I	4.187								
1-I	-4.312	09	-2.33	-1.62	43	-1.62	48	75	66
1-0	4.125								
1-0	-4.250	12	-2.32	-1.83	43	-1.91	49	-1.10	66
2-I	4.438	52	-3.89	32	.44	49	.64	23	.63
2-I	-4.250								
2-0	4.187	29	-3.75	32	.38	58	.57	26	. 56
2-0	-4.125	-1.04	.98	-1.04	-1.41	70	-1.92	26	-2.06
9 <b>-</b> I	4.125	. 29	.64	.52	.34	12	-1.45	55	-4.18
9-I	-4.125	-1.10	-2.21	-1.65	-1.46	-1.31	54	.15	1.53
9-0	4.312	.32	. 70	.52	.38	17	-1.46	61	-4.31
9-0	-4.250								
10-1	4.187	52	95	55	65	06	60	.03	38
10-I	-4.312	38	61	73	46	-1,51	-1.48	70	-2.44
10-0	4.125	41	94	44	65	09	61	03	39
10-0	-4.125	41	62	73	46	-1.51	-1.47	46	-2.40

c = distance from channel centroidal axis to the gauge (+) above and (-) below.

Note: For member number designations see Figure 1.
Predicted values based upon a computer run for 45% fixed-45% fixed arch support conditions.

I = inside arch

O = outside arch

distribution was adjusted slightly to obtain the actual total truck load as weighed while maintaining the same percent weight distribution. As with the initial load test values, predicted member stresses were calculated with both fixed-fixed and pin-pin arch support conditions. It was found that the arch behavior is sensitive to the arch support conditions but that the truss support conditions have little effect upon the arch member stresses. Because of the actual live load compressive stresses in the counters, their area was not reduced in the live load analysis. Finally, new joints were added twelve inches above the lower chord joints to raise the load application point on the vertical members. This change in geometry models the new connections used between the floor beams and hanger rods.




Figure 11: Loaded Hanger Rods - typical for load positions one through four

# Other Tests Conducted

A test was conducted by Brungraber, Kim and Yadlosky on a 1:7 scale model of an actual Pratt truss [2]. The testing of the model truss was part of a study of the

arch-superposition scheme. Truss deflections were measured for the truss alone and for the truss-arch loaded at the same position and weight. A comparison of these deflections showed an average reduction of deflection readings of 30 to 40% with a maximum reduction of 68%. A final test of the truss-arch was conducted with one section of a truss's lower chord completely removed and again with one section of both trusses completely removed. Due to the presence of the arch, catastrophic failure of the bridge in both cases was prevented. The addition of the arches proved to be effective in reducing bridge deflections and preventing catastrophic bridge failure.

A second bridge located in Coudersport, Potter County, Pennsylvania was rehabilitated by the arch-superposition scheme. The bridge, a 73'-2" long, 15'-0" high Pratt truss bridge, was increased from a three-ton capacity to a 20-ton capacity (see Figure 12). A deflection test was conducted both before and after the bridge rehabilitation. The initial test used a seven-ton vehicle with standard H truck wheel spacings and the final test the same vehicle weighing both 7 and 22 1/2 tons. To permit a comparison of the initial test conducted at 7 tons and the final test conducted at 22 1/2 tons, the deflections from the initial test were multiplied by a factor of 4.598, the ratio of the truck rear axle weights (final test/initial test). Table 6 lists the initial and final extrapolated truss deflections


and the truss-arch deflections for the second load and the percent reduction in deflection. The bridge deflection has been reduced an average of 69 percent.

## Discussion

A careful examination of the experimental results from the final load test of bridge number 50 shows there is a fairly even load distribution between the inside and outside arches of each truss. Generally, for the upstream truss the end sections of the outside arch are stressed slightly higher than those of the inside arch. For the downstream truss the more highly stressed arch varies depending upon the load position.

The best correlation between experimental and theoretical values occurs with 40% fixed-40% fixed and 45% fixed-45% fixed arch support conditions for the upstream and downstream trusses respectively. The reduced fixity is due in part to the use of neoprene pads under the steel plates (see Figure 13) which allow some movement to occur. Generally, good correlation between the theoretical and experimental values occurs for the first, second, ninth and tenth arch sections for all four load cases, particularly for the upstream truss.

Table 6: Deflection results from the second bridge to have the arch-superposition scheme installed (inches).



Test	Truck Axle Rear	Weights (lbs) Front
Initial	7,420	6,340
Final - Load 1	7,215	6,145
Final - Load 2	34.120	10.860

		Gai	ıge	
	1	3	2	4
Initial	.058	.064	.093	.083
Final-Load 1	.019	.017	.034	.024
Percent Reduction	67	73	63	71
Extrapolated Initial	. 267	. 294	. 428	.382
Final-Load 2	.095	.080	.140	.111
Percent Reduction	64	73	67	. 71



Figure 12: Looking upstream at a second bridge to have the arch-superposition scheme installed. Coudersport, Potter County, Pennsylvania




Figure 13: Arch end support - steel plates on neoprene pads.

2.1 M. かんかかんのと ログラファイン・1 M. からからという Inc. できないのか

Tables 7 through 9 list the experimental theoretical member stresses and truss deflections ones tested in the initial test allowing a comparison of "before and after" truss stresses and deflections. Inspection of the lower chord stresses indicates little likelihood of tied arch action occuring since the stresses are not significantly higher than predicted by the computer model. The truss deflections are generally larger for the downstream truss. Since the load distribution varies between the two trusses, some variation in deflections is expected. As was the case for the initial test, the theoretical values were calculated with pin-60% pin and pin-50% pin truss supports for the upstream and downstream trusses, respectively. In order to model the "best fit" arch support conditions, 40% or 45% of the 100% fixed arch end moments were input into the computer model as applied moments for the upstream and downstream truss analyses, respectively.

Table 7: Final test experimental and theoretical truss member stresses (ksi) - upstream truss


			Loading Position						
Member		L	_	2		3		-	
Number	Act	Pred	Act	Pred	Act	Pred	Act	Pred	
1	-1.33	.00	64	-1.03	26	54	03	.44	
5	•03	.15	26	58	99	88	-1.07	.38	
6	-1.02	95	17	1.45	1.22	1.19	1.54	.47	
7	. 90	95	2.26	1.45	2.03	1.19	-1.54	.47	
8	12	.00	1.28	2.30	1.13	1.25	.00	-1.13	
9									
10	2.06	1.58	.58	1.87	38	68	64	-1.52	
11	1.54	.00	17	.00	17	.00	23	.00	
12	. 55	08	.90	.52	23	08	.09	1.43	
13	.12	1.06	20	. 26	.93	1.19	.26	04	
14	•03	00	.03	.00	.17	00	.44	.00	
15	-1.33	.03	3.65	3.60	2.15	1.80	.61	-1.59	
16	-3.57	-2.09	-2.09	94	4.90	2.58	2.67	1.86	
17	3.60	2.65	2.35	1.64	-4.03	-1.96	-2.32	-1.59	
18	90	42	23	2.02	1.02	2.77	1.33	-1.47	

STATES OF THE PROPERTY OF THE

Note: For member number designations see Figure 1. Predicted values based upon computer run for 40% fixed-40% fixed arch and pin-60% pin truss support conditions.

			-							42
•										
	Table		l test er str							
	Membe			2	2	Positio	3		4	
•	Numbe		Pred		Pred		Pred		Pred	
	1	-1.22			-1.18		27			
	5	15	.15		67		59		.30	
	6	49	88	.09	.32	.93			:38	
	7	93	88	.09	.32					
	8	03	.09	1.02	1.85	2.09			-1.12	
	9	2.03	1.68	. 61	1.02		98		-1.69	
	10	2.76	1.68	•90	1.02				-1.69	
	11	.93	•00	15	.00	.00	.00			
	12	.20	.09				. 49			
	13	20	1.10			.73	. 28			
	14	.09	•00							
	15	-1.07				2.12			-1.52	
	16		-2.17			6.64			2.02	
	17	5.08				-1.65			-1.83	
	18	.70	40	2.55	2.30	2.47	1.97	/5	-1.16	
		For member Predicted 45% fixed truss sup	value	s base	d upor	compu	iter ru	in for		

Table 9: Final test experimental and theoretical truss-arch deflections (inches)



	Loading Position								
	1	2	3	4					
Gauge	Act Pred	Act Pred	Act Pred	Act Pred					
1	.001016	.049 .070	.084 .078	078037					
2	001014	.080 .072	.123 .052	.034030					
3	.035 .011	.078 .089	.034 .046	006051					
4	.065 .016	.125 .100	.029 .021	020050					

Note: Positive deflection downward. Upstream truss deflections computed with 40% fixed arch supports and pin-60% pin truss supports. Downstream truss deflections computed with 45% fixed arch supports and pin-50% pin truss supports.

というできょうというできます。このからないのできょうというというというというというとは、このからないのでは、このからないのでは、このからないのでは、このからないのでは、このからないのでは、このからないのでは、

Based upon the experimental results obtained, to model the truss-arch action most accurately and safely, the computer model should use:

- (1) pin-pin arch supports for determining the arch stresses
- (2) both pin-pin and pin-roller truss supports to determine the maximum stresses
- (3) full counter cross sectional areas

- (4) reduced truss member cross sectional areas and moment of inertias as previously described in the initial test .
- (5) a load distribution to five hanger rods, the percent of the total H type truck load carried by each rod varying for each load position.

The experimental results also clearly show the H20-44 load capacity of the bridge. The member stresses are well below the maximum allowable for both the trusses and arches. The addition of the arches has increased the degree of certainty of the bridge rating since they add redundancy to the bridge. This redundancy, as shown in the test of the model bridge, has reduced the need to effectively evaluate the capacity of the lower chord pin connections particularily if the arches are designed to carry the H20-44 live load and truss-arch dead load.

# Chapter Summary

The load capacity of Northumberland County bridge number 50 was increased from eight to twenty tons by the addition of steel arches, hanger rods, stringers, floor beams and the replacement of the four existing floor beams. This arch-superposition scheme added a redundancy to the bridge as shown by the model bridge test conducted by Brungraber et al. [2] reducing the need for accurate strength estimates of the lower chord connections. The load test experimental results showed that load sharing between the arches and trusses occurs and members in both are not stressed above the maximum allowable. In order to model the truss-arch action accurately, the computer model should use pinned arch supports and a truck load distributed over five hanger rods on each truss.

# 4. COMPARISON OF INITIAL AND FINAL TEST RESULTS

By testing the bridge both before and after the installation of the arch-superposition scheme, not only can the accuracy of the computer model be checked but the effectiveness of the scheme in carrying and distributing loads can be evaluated. The experimental results from the final test revealed that load sharing between the trusses and arches occurs and that the arches are loaded at five points.

Strains were measured in the same truss members for both tests. Tables 10 and 11 list the percent reduction (or increase) in truss live load member stresses between the initial and final tests at each load position. In order to facilitate this comparison between two tests conducted at different truck loads, the initial test stresses were multiplied by 1.507, the ratio of final to initial total truck weights. A zero percent reduction indicates no change in member stresses while a 100% reduction indicates a zero member stress during the final load test.

The design of the arch-superposition scheme changed the load application point on the interior vertical members. The load is now applied above the lower chord pin causing the member to act as a hanger rod. Therefore, a stress increase in the interior vertical members can be expected for certain load positions. Since the interior vertical

Table 10: Percent reduction (or increase) in truss live load member stresses - upstream truss

Member Number	1	Loading 2	Position 3	4
1	43	65	80	94
5	95	85	65	39
6	10	56	18	41
7	63	49	55	(52)
8	89	56	55	100
9				
10	29	30	33	33
11	78 .			
12	17	(105)	81	80
13	85	70	(7)	13
14	0	. 0	86	90
15		44	51	68
16	9	20	(2)	30
17	(45)	(7)	(46)	33
18	(58)	0	34	38

Note: For member number designations see Figure 1.
Percent reduction calculated using the absolute values of member stresses.

Table 11: Percent reduction (or increase) in truss live load member stresses - downstream truss

Member Number	1	Loading 2	Position 3	4
1	(8)	3	52	48
5	80	46	40	0
6	53	50	29	52
7	66	98	72	0
8	96	62	47	65
9	(283)	(336)	(133)	22
10	40	71	48	(900)
11	82		100	0
12	. 97	0	53	94
13	65	55	(232)	48
14	61	50	78	83
15			59	58
16	(1185)	(160)	(83)	(144)
17	(94)	(128)	(26)	(7)
18	36	(1721)	(119)	56

Note: For member number designations see Figure 1.
Percent reduction calculated using the absolute values of member stresses.

member is still connected to the lower chord chord pin, an increase in the counter tensile stresses can also be expected. Finally, because of the stress increase in the increased lateral interior vertical members and the stability provided by the arches and tension counter, the second counter is able to withstand a greater compressive live load (although the combined dead and live load stress is small). Although increased stresses in the counters can be expected, it should be noted that the arch system is designed to carry the entire H20 live load plus the combined dead loads. Therefore, the increased arch and truss stresses are not critical and do not affect the bridge capacity.

The member stresses in the downstream truss have been reduced an average of 56%. The member stresses in the upstream truss have been reduced an average of 53%.

Similarly, Table 12 lists the percent reduction (or increase) in truss deflections. Gauge 1 is located on the upstream truss, gauge 2 the downstream truss. The truss deflection is reduced an average of 41% for the upstream truss and 80% for the downstream truss. A greater reduction for the downstream truss is expected since the rehabilitation has reduced the effect of the loose lower chord joints of the downstream truss by bypassing them.

The average reduction in truss deflections of 41% and 80% for the upstream and downstream trusses of bridge number

Table 12: Percent reduction in truss deflections.
Positive deflection downwards.

Gauge		1	Loading 2	Position 3	4
	Extrapolated Truss Reading	.045	.130	.151	.056
1	Truss-Arch Reading	.001	.049	.084	078
	Percent Reduction	98	62	44	(39)
	Extrapolated Truss Reading	.048	.301	.342	. 208
2	Truss-Arch Reading	001	.080	.123	.034
	Percent Reduction	- 98	73	64	84

50 straddles the average reduction of 69% found for the second bridge to have the arch-superposition scheme installed. The truss-arch model tested by Brungraber et al.

[2] reduced truss deflections by an average of 30% to 40% with a maximum of 68%.

Clearly, the installation of the arch-superposition scheme has reduced the truss member stresses and deflections.

### 5. SUMMARY AND DISCUSSION

Chapter 2 described the original truss structure and the initial test results. The upstream truss has only one damaged member, and consequently the experimental and theoretical member stresses and truss deflections are in reasonable agreement. The downstream truss has five significantly damaged members and loose lower chord joints. The experimental and theoretical member stresses differed somewhat and the truss deflections were two times greater than expected.

CONTRACTOR AND CONTRACTOR ACCORDING

A computer model of the bridge was found to provide a reasonable estimate of the member stresses. Therefore, it can be used to predict maximum stresses for a bridge rating.

A reasonable correlation between actual and predicted member stresses and truss deflections was found by Sanders et al. [5] and C. P. Heins [6] in tests of various through truss bridges. The predicted values were calculated by a determinate method of analysis assuming ideal pin connections.

Chapter 3 described the arch-superposition scheme and the final test results. The experimental results showed that sharing of the applied live load between the arches and trusses occurs. Also, the load distribution to the four arches is fairly even. The arch end supports are acting as 40% or 45% rotationally fixed bearings, due in part to the

neoprene pads placed under the steel bearing plates which allow some movement.

Comparing the final test truss actual member stresses with the initial test stresses (multiplied by 1.507 to account for the difference in truck weights between the two tests), show an average reduction of 53% and 56% for the upstream and downstream trusses, respectivly. The truss deflections are reduced by an average of 41% (upstream) and 80% (downstream). The truss results also show no tied arch action occuring since the lower chord tensile stresses are not higher than predicted by the computer model.

A computer model was developed providing a reasonable correlation between the actual arch and truss stresses and the predicted values. It is recommended for design purposes when determining maximum member stresses, to assume a pin-pin arch support condition and both pin-pin and pin-roller truss support conditions. These maximum member stresses can then be used to design the arch section and check the adequacy of the truss members.

Located in Coudersport, Potter County, Pennsylvania, the second bridge to have the arch-superposition scheme installed was tested resulting in a 69% average reduction in truss deflections. The test of a model truss bridge by Brungraber et al. [2] resulted in an average reduction of 30% to 40% in truss deflections after the arches were installed. Also, to demonstrate the redundancy introduced

by the arches, two tests were conducted on the model. In the first test, one truss lower chord member was removed (to simulate a failure). In the second test, one lower chord member was removed from both trusses. Although the bridge deflections increased, catastrophic failure was prevented by the arches.

The load testing and rehabilitation of Northumberland County bridge number 50 have demonstrated that the bridge capacity has been increased to H20-44 inventory and the scheme can be installed with just minimal traffic delays. This has been achieved at a considerably lower cost than would be incurred for a new structure built to today's specifications.

The total project cost, including all materials, fabrication and field work was \$34,000. A replacement bridge would have to be 32 feet wide (two ten foot lanes plus six foot shoulders). For estimating purposes a cost of \$110 per square foot is a reasonable value (1983) [9]. Therefore, it is estimated that a new bridge would cost \$250,000, approximately seven times more than the arch-superposition scheme. Both the scheme and the new bridge result in 20 ton bridge load capacities.


For further details on estimating the cost of installing the arch-superposition scheme to truss bridges of varying length, see reference 9.

Several other methods to increase the load capacity of

through truss bridges have been studied [8]. These are:

- (1) stiffening of the top chord compression member
- (2) prestressing of the lower chord with cables strung from the end supports
- (3) shifting of the end supports
- (4) adding a central support

Stiffening of the top chord is achieved by shortening the span length and thus reducing the slenderness ratio. For a Warren truss this is done by creating subpanels by adding the vertical members as shown in Figure 14.







Figure 14: Stiffening of the top chord to increase bridge capacity.

Prestressing of the lower chord with a compressive force removes the dead load stress from the lower chord and results in lower live load tensile stresses. For a Warren truss prestressing is achieved by stringing a cable between the end supports and placing vertical struts between this cable and the lower chord as shown in Figure 15.






Figure 15: Prestressing of the lower chord to increase bridge capacity.

Shifting of the end supports inwards reduces the effective bridge span length and thus the member forces by as much as 40% to 50% (see Figure 16). Addition of a central support halves the span length while maintaining the span continuity.




Figure 16: Shifting of the end supports to increase bridge capacity.

Although they are inexpensive when compared with the cost of a new bridge, there are several problems with the truss strengthening methods discussed so far. The determination of connection strengths remains critical. Even after completion of the work, maintenance of the truss members and connections is very important. Therefore, the difficulty in determining the bridge rating will remain. Finally, the improvement in load capacity is limited. With at most a 50% improvement in strength expected by any of the schemes, the truss must be rated at 13 tons prior to rehabilitation in order to achieve a 20 ton load capacity.

The arch-superposition scheme has been demonstrated to be effective in increasing the truss and roadway load capacities. Because of the redundancy provided by the arches, the risk of catastrophic failure is reduced.

#### 6. CONCLUSIONS

Based upon the load testing and field work completed, the arch-superposition scheme applied to Northumberland County bridge number 50 was:

- (1) structurally effective. The bridge load capacity was increased from H8-44 to H20-44.
- (2) economically effective. The scheme cost a total of \$34,000 as compared with \$250,000 for a new bridge built to today's specifications.
- (3) easily installed. Rehabilitation required 15 days using a two and three man crew.
- (4) non-disruptive. The maximum traffic delay during the 15 day construction period was 15 minutes.

The results from tests conducted on the two truss-arch bridges and the model bridge indicate that a 50% average reduction in member stresses and truss deflections can be expected after the arch installation. Further, the arches provide a redundancy to the bridge as demonstrated in the model testing. The scheme is considered to be readily adaptable to truss bridges with various span lengths, heights, widths, and number of spans.

#### BIBLIOGRAPHY

- (1) Wilbur Smith and Assoc., Bridge Deficiencies in the States: An Overview of the Problem, Wilbur Smith and Assoc., Pittsburg, May, 1982.
- (2) Brungraber, R. J., Kim, J. B., Yadlosky, J. M., "Truss Rehabilitation by the Use of Steel Arches", Report to AISI, Civil Engineering Department, Bucknell University, Lewisburg, Pennsylavania, 1982.
- (3) AASHTO (1978), Manual for Maintenance Inspection of Bridges, Third Edition, American Association of State Highway Transportation Officials, Washington, D.C..
- (4) AASHTO (1977), Standard Specifications for Highway Bridges, 1977, Twelfth Edition, American Association of State Highway and Transportation Officials, Washington, D.C..
- (5) Sanders, W. W., Elleby, H. A., Klaiber, F. W., "Ultimate Load Behavior of Full-Scale Highway Truss Bridges, Summary Report", Engineering Research Institute, Iowa State University, Ames, September 1975.
- (6) Heins, C. P., "Bridge Evaluation by Field Testing", Proceedings of an International Conference on Rehabilitation of Buildings and Bridges Including Investigations, December 1981, ed. Gajanan M. Sabnis (Washington, D.C., 1982), pp. 182-84.

- (7) Rosen, A., Schmit, L., "Design Oriented Analysis of Imperfect Truss Structures Part I Accurate Analysis", International Journal for Numerical Methods in Engineering, Vol 14, 1979, pp. 1309-21.
- (8) Sabnis, G. M., Cayes, L., Modi, H., "Innovative Methods for Upgrading Structurally and Geometrically Deficient Through Truss Bridges", Proceedings of an International Conference on Rehabilitation of Buildings and Bridges Including Investigations, December 1981, ed. Gajanan M. Sabnis (Washington, D.C., 1982), pp. 221-27.
- (9) Paino, P., "A Case Study for the Rehabilitation of a Steel Truss Bridge Using a Superimposed Arch System", a thesis presented to the faculty of Bucknell University, Lewisburg, Pennsylvania, September, 1983.


# APPENDICES

# Appendix 1: Bridge Rating Calculations

#### Nomenclature

b = length of member base (inches)
d = length of member height (inches)
FB = allowable bending strength (lbs/sq. inch)
fv = actual shear stress (lbs/sq. inch)
FV = allowable shear stress (lb/sq. inch)
FY = yield stress of the steel (lb/sq. inch)
L = span length (inches)
MD = dead load moment (lb-in)
ML = live load moment (lb-in)
MDL = dead plus live load moment (lb-in)
P = wheel load
S = average stringer spacing (feet)
SX = section modulus (cubic inches)
w = uniform load (lb/ft)

Note: Bridge rated by the allowable stress method from the "Manual for Maintenance Inspection of Bridges, 1978"



### TIMBER DECK ANALYSIS

Use the following maximum allowable stresses:

$$FB=(1.33)x(1200)=1596$$
  $FV=120$ 

For 2 x 4 inch planks: 
$$SX = (b)x(d)x(d)/6$$
  
=  $(1.5)x(3.5)x(3.5) = 3.06$ 

MDL = (SX)x(FB) = (3.06)x(1596) = 4884

Timber Dead Load = (1.5)x(3.5)x(1)x(50)x(1/1728) = 0.151b/in

MD = (w)x(1)x(1)/8 = (.15)x(24)x(24)/8 = 11.0

ML = 4884-11 = 4873

Distribution of Wheel Loads

Area of Contact:

Normal to Direction of Span = 15" Direction of Span H10 = 14", H15 = 17", H20 = 20" (based upon the equations: Area = .01P, L/W = 1/2.5)

ジャンチンとは、国内のアンスのでは、アンスののは、国内のアンスののでは、国内のアンスのは、国内のアンスのでは、国内のアンスのでは、国内のアンスのは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国内のアンスのでは、国

By trial and error:

H15 A = 
$$(17)x(15)$$
  
M =  $(P/A)x(1.5)x(17/2)x(24/2)-(P/A)x(1.5)x(8.5)x(4.25)$   
= 4873  $(.39)xP = 4873$   
P =  $12,575 > 12,000$ 

Check Shear

SOOT ACCOUNTS HANDS SOUTH TO SEE A TOWN TO SEE SOUTH TO SEE SEED AND SEED OF THE SEE SOUTH TO SEE SOUTH TO SEE SEED OF THE SEE

fv = ((3)x(V))/((2)x(b)x(d))V = ((12,000)/A)x(1.5)x(17/2) = 600fv = ((3)x(600))/((2)x(1.5)x(3.5)) = 171 > 120 = FV

Shear controls. The allowable load is less than 15 tons.

HIO A = 
$$(14)x(15)$$
 P = 8,000  
V =  $((8,000)/A)x(1.5)x(14/2)$  = 400  
fv =  $((3)x(400))/((2)x(1.5)x(3.5))$  = 114 < 120

TIMBER DECK IS RATED AT HIO OPERATING

STRINGER ANALYSIS

Use the following values:

L=175 S=2 FB=(1.33)x(1200)=1596 FV=120

Live load distribution to stringer = (2/4)x(P)

SX = (6)x(12)x(12)/6 = 144

MDL = (144)x(1596) = 229,824

Total dead load = 39.58 lb/ft

Deck: (3.5/12)x(1)x(50) = 14.58 lb/ft Stringer: (6/12)x(1)x(50) = 25 lb/ft (unit weight of timber = 50 lb/cu. ft)

MD = (39.58/12)x(175)x(175)/8 = 12,626

ML = (2/4)x(P)x(1)/4 = 229,824-12,626P = 9,930


9,930/.8 = 12,411

Check shear for H12

V = (9600)x(2/4) = 4800fv = ((3)x(4800))/((2)x(6)x(12)) = 100 < 120 O.K.

STRINGERS ARE RATED AT H12 OPERATING

FLOOR BEAM ANALYSIS




Use an impact factor of 1.3

Total ML(max) = (1.3)x(68.85xP) = 89.51xP

Total Dead Load on Floor Beam: 259.4 lb/ft

Deck: (3.5/12)x(14.58)x(50) = 212.68 Stringers: (6/12)x(14.58)x(50) = 21.3Approximate Floor Beam: (8.15/144)x(450) = 25.5(unit weight for cast iron is 450 lb/cu. ft)

MD = (21.6)x(205.5)x(205.5)/8 = 114,022



Existing floor beam dimensions as measured in the field.

Moment of Inertia = 177.6 IN

$$SX = 177.6/6 = 29.6$$

FB = (.75)x(FY) = (.75)x(26,000) = 19,500(For operating rating only)

MDL = 
$$(19,500)x(29.6) = 577,200$$
  
 $(68.85xP)+(114,022) = 577,200$   
P = 6,727

6,727/.8 = 8,400

Check shear for H8 loading

FV = (.45)x(FY) = 11.700 fV = P/A = 6.400/((12)x(.375)) = 1.422 < 11.700 O.K. FLOOR BEAMS ARE RATED FOR H8 OPERATING

$$FB = (.60)x(FY) = (.6)x(26,000) = 15,600$$
  
(For inventory rating)

$$(68.85xP)+(114,022) = 461,760$$
  
P = 5050

5050/.8 = 6,300

FLOOR BEAMS ARE RATED FOR H6 INVENTORY

Since the floor beams have the lowest operating rating among the deck, stringers, and floor beams, the bridge is rated at 8 tons operating and 6 tons inventory.

Appendix 2: Sample Computer Output

(1)	Load	Position	2	_	Upstream	truss	with	pin-pin	supports
-----	------	----------	---	---	----------	-------	------	---------	----------

E to	or s	structure	ctu	a				
20.5	00000	2						
2								
10							•	
7	×	_		X-Coor	1	X-Reaction	Y-Reaction	2-Reaction
-	-	_		0.000	0.0000	5.7444	.5.9920	•
~	0	C		175.00	192.00	0.0000	0.0000	0.0000
M	C	ی		350.00	$\sim$	000000		•
7	0	Ö		525.00	192.00	0.000.0		000000
S	0	0	0	200.00	92	000000	0.000.0	000000
9	-	_		875.00	0.0000	-5.7444	•	•
7		0	0	700.00	0.0000	0.000	0.0000	0000.0
∞	C	0	ပ	25.0		0.000.0		0000.0
0	0	0	၁	350.03	0.0006	0000.0	0.0000	0000.0
10	0	0	0	175.00	0.0000	0.00.0	c.	0.0000
Σ								
13								
Mea	7	×		4	$\subset$	3 t	000	NIS
-					S	259.79	729.	.739
2	~:	~		2.6200	S	175.00	1.000	000.
M	~			•	S	0.	1.000	000.
7	7			7.0200	25.660	5	1.000	000.
S	~			7.6200		259.79	729.	739
9	7			1.9000	ш	. 175	1.000	000
~	(II)			1.9000	-10000E-	175.0	1.000	.000
∞	6			2.8500	-10000E-	3 175.0	1.000	000.
0	10			1.9060	-10000E-	175.0	1.000	000
10		_		1.9000	-10000E-	03 17	1.000	000.
11	2			1.7600	-10000E-	0.	000.	1.000
12	0			3.0000	7.2900	2.0	000.	1.000
13	0,			3.0000	7.2900	CJ	000	1.000
14	2			1.7600	1	03 192.0	000	. 000 .
15	2			2.0000		03 259.7	729.	739
16	~	က		1.0000	.10000E-	1.6	2674	739
17	0			1.ບວິນປ	-10000E-	2.5	929.	. 739
18	20	^		2.3900	-1000001-		729.	.739

### Truss with pin-pin supports - page 2

```
.37403E-05
                                                                                                                                                                                                                                                                               -.50644E-05
                                                                                                                                                                                                                                                                                        -.18927E-04
                                                                                                                                                                                                                                                                                                 -.13640E-04
                                                                                                                                                                                                                                            3.2506
                                                                                                                                                                                                                                                    .98529
                                                                                                                                                                                                                                    -1.8848
                                                                                                                                                                                                                                                              -1.6505
                                                                                                                                                                                                                                                                                        .27161E-06
                                                                                                                                                                                                                                    .72552E-02
                                                                                                                                                                                                                                            -.29345E-01
                                                                                                                                                                                                                                                     .10399E-01
                                                                                                                                                                                                                                                              .19189E-01
                                                                                                                                                                                                                                                                      -.63531E-02
                                                                                                                                                                                                                                                                               .11409E-07
                                                                                                                                                                                                                                                                                                  .13937 E-06
                                                                                                                                                                                                                             K-Shear
                                                                                                                                                                                                                                            -10.906
                                                                                                                                                                                                                                                                     -6.8390
                                                                                                                                                                                                                                                                              -1.1529
                                                                                                                                                                                                                                    -3.1142
                                                                                                                                                                                                                                                     -10.046
                                                                                                                                                                                                                                                              -9.1568
                                                                                                                                                                                                                                                                                       -1.1529
                                                                                                                                                                                                                                                                                                4.2730
                                                                                                                                                                                                                            K-Axial
                                                                                                                                                                                                                                    -05
                                                                                                                                                                                                                                                                              .306788-05
                                                                                                                                                                                                                                                                                       -.28604E-04
                                                                                                                                                                                                                                                                                                -.10837E-04
                                                                                                                                    -.33011E-03
                                                                                                                                                     . 25596E-03
                                                                                                                          -. 12077E-04
                                                                                                                                           -.17487E-03
                                                                                                                                                              .26247E-03
                                                                                                                                                                      -.16020E-0.4
                                                                                                                                                                               .22117E-03
                                                                                                                                                                                        -.61095E-04
                                                                                                                                                                                                 .20073E-04
                                                                                                                                                                                                         -.25983E-03
                                                                                                                                                                                                                                   -.68549E
                                                                                                                                                                                                                             J-Noment
                                                                                                                    Rotational
                                                                                                                                                                                                                                                            -1.7077
                                                                                                                                                                                                                                            1.8848
                                                                                                                                                                                                                                                    -2.8051
                                                                                                                                                                                                                                                                     1.6504
 RotLoad
         0.0000
                  0.0000
                                                                                                                                                                                                                                   -.72552E-02
                                                                                                                                                                                                                                            .29545E-01
                                                                                                                                                                                                                                                    -.10399E-01
                                                                                                                                                                                                                                                                                       -.27161E-06
                                                                                                                                                                                                                                                                                                -.13987E-06
                                                                                                                                                                                                                                                             -.19139E-U1
                                                                                                                                                                                                                                                                     .03531E-02
                                                                                                                                                                                                                                                                              -.11409E-U7
                                                                                                                                                     -.76145E-01
                                                                                                                                                              -.19649E-01
                                                                                                                                                                                       -.7407UE-U1
                                                                                                                                                                                                 -.91376E-01
                                                                                                                                                                                                         -. 63838E-03 -. 28063E-01
                                                                                                                                             -.39274E-U1
                                                                                                                                                                               .35397E-02 -.19649E-01
                                                                                                                                    -.28063E-01
                                                                                                                                                                                                                           J-Shear
                                                                                                                   Vertical
                                                                                                                                                                       000000
                                                                                                                           0.000.0
 Verttoad
        -3.1000
                  -7.9200
                                                                                                         Joint Displacements
                                                                                                                                                                                                                   Member-End Actions
                                                                                                                                                                                                 -.16768E-P2
                                                                                                                                    .15730E-01
                                                                                                                                                     -.14804E-G2
                                                                                                                                                              -. 20893E-02
                                                                                                                                           .58679E-02
                                                                                                                                                                                        . 70794E-02
                                                                                                                   Horizontal
                                                                                                 Uniform
                                                                                                                                                                                                                           J-Axial
                                                                                                                                                                                                                                                             9.1565
                                                                                                                                                                                                                                                                      0.8090
                                                                                                                                                                                                                                                                              1.1529
                                                                                                                                                                                                                                                                                       1.1529
                                                                                                                                                                                                                                   3.1142
                                                                                                                                                                                                                                            10.906
                                                                                                                                                                                                                                                     10.046
                                                                                                                                                                                                                                                                                                -4.2730
                                                                                                                                                                      0.000.0
         9.0000
                 0000.0
Jt HorLoad
                           NULFI
                                                                                                                                                                                                                          HEN
                                                                                                                                    10 O
                                                                                                                                                                                                                                    25301
                                                                                                                                                                                                                                                                                9~ 8
```

CONTRACTOR CONTRACTOR

Truss with pin-pin supports - page 3

.2730728472E-0620104E-042730728689E-0767575E-0551768E-0765575E-0651768E-04985312730527205E-0232168E-04985313762E-0232168E-04985353762E-0251792E-0615859E-074782E-074782E-074782E-074782E-074782E-074782E-074782E-074782E-074782E-051033E-074782E-054802E-024813E-024813E-024813E-0214295E-0614295E-0614295E-0614295E-0614295E-0614295E-061437215100E-0749001437215100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0715100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-0755100E-07		
27307 517686-05202776-06133676-0 98531 232056-02321686-0 96325 .171926-06158596-0 .0673171926-06158596-0 .0673317626-0747826-0 .3152317626-0747826-0 .3152461296-0747836-0 .3152461296-0747836-0 .431112586-0 .431112356-0 .448136-02490 .49046-0397846-0 .49046-03904996-0390681 .27326-06142956-06142956-06142956-06142956-06142956-06142956-06142956-06142956-06142956-07490 .14372151006-07490 .1437215216-06152846152846-0715284419326-031933919326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0719326-0	4 27307	8472E-06 .29722E-0
\$1768E-0520277E-0618367E-0  9853123205E-0282168E-0  11763E-05 .17192E-06 .15859E-0  10673 .31762E-07 .74782E-0  2794831762E-07 .41689E-0  277246129E-07 .41689E-0  277246129E-07 .41689E-0  277246129E-07 .41689E-0  277246129E-07 .41689E-0  277246129E-07 .41689E-0  277310335E-0241  284427335E-0249  29414E-0511521E-0615  29414E-0511521E-0615  29414E-0511521E-0615  2033915881E-0797  2735615881E-0715  273615881E-0715  2737615881E-0715  2737615881E-0715	- 57307 -	8689E-0717369E-0
853123205E-02 -6037E-0 6325 -37626E-02 -6037E-0 1763E-05 -17192E-06 -15859E-0 1767234257E-07 -74782E-0 279434257E-07 -41689E-0 2794346129E-07 -41689E-0 277246129E-07 -41689E-0 277246129E-07 -41689E-0 253614813E-0241 431114813E-0241 253614813E-0241 253614813E-0241 253614895E-0614 277214295E-0614 277314295E-0614 277311521E-0614 284477350E-0315 284477350E-0315 277484257E-0753	4 .51768E-05	0277E-0620564E-0
6325 17626-02 .603776-0 17636-05 .171926-06 .158596-0 2794342576-07 .747826-0 2794342576-07 .416896-0 2792461296-07416896-0 2772461296-07972846-0 2772461296-07972846-0 2773418026-0214 2314148136-0214 2314273356-0214 2314273356-0390 2681600476-0860 268149856-0614 284415216-0611 284415216-0611 284415216-0611 284415216-0611 2844153506-0377 2108153506-0377 2108153506-0715 2794158816-0715	4 .93531	.44550
1763E-05 .17192E-06 .15859E-0 2794 .31762E-07 .74782E-0 2794 .33013E-07 .41689E-0 3152 .46129E-07 .41689E-0 2772 .46129E-07 .97284E-0 2772 .46129E-07 .97284E-0 2773 .41802E-02 .10 4311 .1589E-02 .14813E-02 .14813E-02 .14813E-02 .14813E-02 .14813E-03 .14813E-03 .14813E-03 .14813E-03 .14813E-07 .14813E-07 .14813E-07 .14813E-07 .14813E-07 .1881E-07 .	4 96325 -	7626E-02 .72236
0678 -31762E-07 -74782E-0 2794 -34257E-07 -41689E-0 3152 -46129E-07 -97284E-0 -46129E-07 -97284E-0 -46129E-07 -97284E-0 -46129E-07 -97284E-0 -10335E-02 -14 4311 -10335E-02 -41 4314 -27335E-02 -90 681 -60047E-08 -60 681 -14813E-02 -41 4372 -14813E-02 -90 681 -14813E-02 -90 681 -14813E-02 -90 6831 -14813E-02 -90 6831 -14813E-02 -90 6831 -14813E-02 -90 6831 -11521E-06 -115 6833E-06 -115542E-02 -90 6833E-06 -115542E-02 -90 6833E-06 -115542E-02 -90 68339 -84257E-07 -90 68339 -90	4 .11753E-05 -	7192E-06 .17149E-0
279446257E-U712258E-0 315246129E-0797284E-0 5 277246129E-0797284E-0 5 27246129E-0797284E-0 5 27246129E-0797284E-0 5 25641802E-0241 431114813E-0241 431114835E-0241 437227335E-0390 68149077E-0749 437214985E-0614 437215100E-0715 584477350E-0315 584577350E-0315 5835E-0617 584677350E-0315 5835E-0617 584777350E-0315 5835E-0617 58481E-0715 584815-0715 584815-0753 5855E-0753	7 3.0678 -	1762E-07 .81764E-0
3152	4 -1.2794	4257E-0796306E-0
277246129E-0797284E-0 e Stresses and Moment on Member al J-Shear or Member 155910335E-0214 304427335E-0227 699490499E-0390 068160047E-0860 068147295E-0614 437214295E-0614 437215100E-0749 43721550E-0377 21081550E-0377 210815542E-0615 6833E-C697680E-0715 6833E-C697680E-0715 6833E-0615 6833E-0615881E-0715 6833E-0615881E-0715 6833E-0615881E-0715	5 1.3152 -	3013E-07 .96032E-0
e Stresses and Moment on Member 155910335E-0210 553614813E-0241 431127335E-0290 699490499E-0390 14295E-0614 437249077E-0714 437211521E-0615 6833E-C617550E-0315 6833E-C615881E-0797 6833E-0615881E-0793	5 6.7772	6129E-0722554E-
al 1559 -10335E-02 -14802E-02 -14813E-02 -14813E-02 -14813E-02 -14813E-02 -14813E-02 -14813E-02 -14813E-03 -14813E-03 -14813E-03 -14813E-03 -14813E-03 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-06 -11521E-		
155910335E-0210 431114813E-0241 304427335E-0241 699490499E-0390 068114295E-0614 501149077E-0749 437215100E-0715 43721550E-0617 284477350E-0377 210812542E-0715 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0615 6833E-0715	ear Maxim	um Roment
553641802E-0241813E-0214813E-0214813E-0214813E-0214813E-0214813E-0214813E-0214813E-0390499E-039068114295E-0614295E-0614985E-0615100E-0715100E-0715100E-071521E-0615242E-0215242E-0215242E-0315242E-0315242E-0715242E-07152525E-0315242E-0715242E-0715252E-0715252E-0715252E-0715252E-0715252E-0715252E-0715252E-0715252E-0715252E-0715252E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E-07533013E	335E-02 1.88	သ
431114813E-02 .14 304427335E-02 .27 699490499E-0390 068114295E-08 .60 068114295E-06 .14 501149077E-07 .49 4372 .15100E-0715 210877350E-03 .77 210877350E-03 .77 210877350E-03 .77 21087350E-03 .77 21087350E-03 .77 21087350E-03 .77 21087350E-03 .77 21087350E-03 .77 2154215881E-0715881E-0715881E-07 .15881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E-0715881E	802E-02 3.25	90
3044 -27335E-G2 -90499E-03 -60047E-08 -60047E-08 -14295E-G6 -144295E-G6 -144295E-G6 -14425E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6 -11521E-G6	8136-02 2.80	51
699490499E-0390 068160047E-08 .60 068114295E-06 .14 501149077E-07 .49 4372 .15100E-0715 24477350E-03 .77 210877350E-0315 6833E-06 .115242E-0715 6833F-06 .15881E-0797 033984257E-0797	335E-02 1.70	77
0681 14295E-06 .14295E-06 .14985E-06 14985E-06 14985E-06 15100E-07 15100E-07 1521E-06 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17351E-06 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 17350E-03 	4996-03 1.65	7
068114295E-U614 437214985E-0614 437215100E-0715 437215100E-0715 210811521E-0611 284477350E-0377 210812542E-0212 6833E-C6 .97680E-0797 033984257E-0797 315253013E-0753	047E-08 .506	4E-0
\$011 -,49077E-07 -,14985E-06 -,14985E-06 -,14985E-06 -,14985E-06 -,15100E-07 -,15100E-07 -,1520E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03 -,77350E-03	295E-06 .286	46-0
4372 .14985E-0614 4372 .15100E-0715 284477350E-03 .77 2108 .12542E-0212 6833E-C6 .97680E-0797 033984257E-0797 3152 .53013E-0753	077E-07 .136	0-30
4372 .15100E-0715 9414E-0511521E-06 .11 284477350E-03 .77 2108 .12542E-0212 6833E-C6 .97680E-0797 033984257E-0795 3152 .53013E-0753	985E-06 .297	26-0
9414E-0511521E-0611 284477350E-0377 210812542E-0212 6833E-C6 .97680E-0797 033915881E-0797 279484257E-0784	1006-07 .675	75E-05
9414E-0511521E-06 .11 284477350E-03 .77 2108 .12542E-0212 6833E-C6 .97680E-0797 0339 .15881E-0715 279484257E-07 .84		
9414E-0511521E-06 .11 284477350E-03 .77 2108 .12542E-0212 6833E-06 .97680E-0797 0339 .15881E-0795 2794 .53013E-0753		
9414E-0511521E-0611 284477350E-0377 2108 .12542E-0212 6833E-C6 .97680E-0797 033915881E-0797 279484257E-0784		
284477350E-03 .77 2108 .12542E-0212 6833E-06 .97680E-0797 0339 .15881E-0797 279484257E-07 .84 3152 .53013E-0753		
284477350E-03 .77 2108 .12542E-0212 6833E-06 .97680E-0797 0339 .15881E-0715 279484257E-07 .84 3152 .53013E-0753	521E-06 . 205	64E-04
2108 .12542E-0212 6833E-06 .97680E-0797 0339 .15881E-0715 279484257E-07 .84 3152 .53013E-0753	350E-03 .445	0
6833E-C6 .97680E-0797 0339 .15881E-0715 279484257E-07 .84 3152 .53013E-0753	542E-02 .722	
0339 .15881E-0715 279484257E-07 .84 3152 .53013E-0753	680E-07 .171	9E-0
279484257E-07 .84 3152 .53013E-0753	881E-07 .817	46-0
3152 53013E-0753	257E-07 .122	8E-0
7502	013E-07 .960	
3886 C3U03E-U/ . C3	065E-07 .972	0-35

- Upstream truss with pin-roller (2) Load Position 2 supports 0.0000 0.0000 .74374E-04 -.66656E-04 2-Reaction 0.0000 0.0000 0000.0 0.0000 -.739 .000 .739 .000 .000 .000 .000 000 000 .000 .000 .739 .000 .000 -.739 Y-Reaction .000 000 .000 000 000 .674 000 000 429. .674 419 0.0000 0.0000 0.00000 5.9920 000000 0.000.0 0.000.0 192.00 -. 90837E-04 259.79 175.00 75.00 175.00 959.79 75.00 175.00 75.00 175.00 175.00 92.00 92.00 259.79 259.79 259.79 ength-259.79 X-Reaction 0.0000 0.0000 0.0000 0.0000 0.000.0 0.0000 000000 0.0000 .10000E-03 .10000E-U3 .10000E-JS .10000E-03 .10000E-03 .10000E-03 10000E-03 .10000E-03 :10000E-03 ,1000GE-03 Inertia 25.660 25.660 25.660 25.660 .2900 7.2900 25.660 192.00 192.00 192.00 0.00000 0.0000 Y-Coor 0.0000 192.00 0.0000 0.0000 7.0200 ,0200 .9000 1.0000 350.00 525.00 700.00 7.0200 7.0200 .9000 1.0000 0.000 175.00 200.007 875.00 525.00 350.00 7.0200 .9000 .8500 0006. 1.7600 .0000 3.0000 1.7600 2.0000 X-Coor 2.0000 00-0000-00

4 C 8 O O N M 4 N O 8 A A

3 P N M G 70

9

01001

E for structur

30006.00

10

0000-0000

00000000

Mea

## Truss with pin-roller supports - page 2

```
-.35694E-04
                                                                                                                                                                    .16267E-04
                                                                                                                                                                              -.16220E-04
                                                                                                                                                                                                -.12147E-04
                                                                                                                          K-Moment
                                                                                                                                                  1.0060
                                                                                                                                                           -.68075
                                                                                                                                 -.91508
                                                                                                                                          3.1775
                                                                                                                                                                            .23472E-06
                                                                                                                                                                                     .41137E-06
                                                                                                                                                           .13230E-01
                                                                                                                                                                                               .13937E-06
                                                                                                                                 .35225E-02
                                                                                                                                          -.23386E-01
                                                                                                                                                  .10399E-01
                                                                                                                                                                    -.26204E-02
                                                                                                                          K-Shear
                                                                                                                                 -3.1108
                                                                                                                                           -10.906
                                                                                                                                                   -10.300
                                                                                                                                                           -9.1572
                                                                                                                                                                    -6.8056
                                                                                                                                                                             4.5864
                                                                                                                                                                                      4.5364
                                                                                                                          K-Axial
                                                                                                                                  -.19994E-04
                                                                                                                                                                             -.24856E-04
                                                                                                                                                                                      -.36296E-04
                                                                                                                                                                                               -.12330E-04
                                 -.43438E-03
                                          -.17722E-03
                                                   .25832E-03
                                                                    . 25187E-03
                                                                                      -.17551E-04
                         -.27997E-03
                                                            .36674E-03
                                                                                              -.22871E-04
                                                                                                                          J-Noment
                  Rotational
                                                                                                                                                                    .68073
                                                                                                                                          .91509
                                                                                                                                                  -2.8258
                                                                                                                                                            -1.6346
                                                                             0.0000
                                                                                                        0.0000
                                                                                                                                                                            -.23472E-U6
                                                                                                                                 -.35225E-02
                                                                                                                                                  -.10399E-01
                                                                                                                                                                                     -.41137E-U6
                                                                                                                                                                                              -.13987E-06
                                                                                                                                          .23386E-01
                                                                                                                                                           -.13230E-01
                                                                                                                                                                    .26204E-02
                                 -.65397E-01
                                                                                                       .16783E-01 -.65397E-01
                                                            -.56983E-01
                                                                             -.56983E-01
                                                                                                                          J-Shear
                Vertical
                                          -.13248
                                                  -.11935
                                                                    0.0000
                                                                                      -.11669
                         0.0000
                                                                                              -.13397
        Displacements
                                                                                                                r-End Actions
                                  56897E-01
                                           .47334E-01
                                                   .39275E-01
                                                            31666E-01
                                                                             .67640E-01
                                                                                      .53559E-01
                                                                    .31721E-01
                                                                                              .33565E-01
                Horizontal
Uniform
                                                                                                                                                  10.300
                                                                                                                         J-Axial
                                                                                                                                          10.906
                                                                                                                                 8.1108
                                                                                                                                                            9.1572
                                                                                                                                                                     6.8056
                                                                                                                                                                             -4.5864
                                                                                                                                                                                     -4.5864
                                                                                                                                                                                               -9.7634
                        0.000.0
        Joint
                                                                                                                Memb
                                                                                                                         MEM
                                 0 9 8 4 6 V 8 4 O
                                                                                                                                  - NM 4 5 9 N 8
```

0.000.0 0.0000

RotLoad

VertLoad -3.1000 -7.9200

Jt Horload 0.0000 0.0000

NULM

0

# Truss with pin-roller supports - page 3

-5.4664 97623E-05 70068 1.2479 85281E-05 -8.0759 -9.0238 -1.6922 -6.7853	80672E-06 .1 80672E-08 .6 18318E-023 .32739E-02 .6 39057E-086	19239E-04 5.4664	27473E-06 -05 .80672E-03	-28838E-04
7623E-0 0068 2479 6281E-0 0759 0238 6922	80672E-08 18318E-02 32739E-02 39057E-08 83080E-08	5676 0767	-05 .80672E-0	75616E-Ü
0068 2479 5281E-0 0759 0238 6922 7853	18318E-02 32739E-02 39057E-08 83080E-08	016/6-02 .7/063		10000
2479 6281E-0 0759 0238 6922	32739E-02 39057E-08 83080E-08	6590E-04 .7006	18318E-0	3516
6281E-0 0759 0238 6922 7853	39057E-08	4699E-04 -1.247	.32739E-0	.6285
0759 0238 6922 7853	33080E-03	105 2E -05 .86 28	-05 .39057E-0	.535536
023 692 785		6729E-05 8.075	83080E-0	.58312E-0
692 785	82478E-07	2557E-04 9023	82478E-0	88694E-0
785	51234E-07 .	4078E-05 1.692	51234E-0	.99021E-0
	.22676E-07	3832E-05 6.785	.22676E-0	.14922E-0
e Stress	and Moment o	ile in 5 e		
al	-Shea	hear	x imu	
155	50178E-0	. 50178E-0	1508	
553	.333136-0	.33313E-0	.177	
197	.14813E-0	14813E-0	.825	
304	20	.18847E-02	1.6346	
769	.37328E-D	37328E-0	807	
413	.12354E-0	.12354E-0	24856E-0	
413	21651E-0	21651E-0	36296E-0	
127	49077E-0	49077E-0	12330E	
877	23537E-0	23537E-0	9523E-0	
877	4459E-0	14459E-0	28838E-0	
0	0-076007	0-036637	24145	
0 10	0-300004.	0-30004	70105	
3326	61060E-U	61060E-0	5510	
1596	10913E-0	10913E-0	62853	
206	22191E-0	22191E-0	61052E-0	
38	41540E-0	1540E-0	58312E-0	
90238	32478E-07	.82478E-07	.12557E-04	
269	51234E-0	51234E-0	99021E-0	
392	1338E-U	11338E-0	3332E-0	

(3) Load Position 2 - Upstream truss-arch with pin-pin arch supports

	2-Reaction	•	•	•	•	0,0000	•	•	.52322E-03	.45858E-04	32219E-03	0000.0	63552E-04	000000	0-	.85290E-04	23457E-0	0.000.0	0000000	0.000.0	000000	.000	•	0.000.0	.000	000.	000000	•	.000	0.	0.000.0
	O	.866	.000	.000	.000	0.000	.297	•	0.0000	●	•	•	0.0000	•	•		•	•	•	000000	•	0.0000	•	•	00	0.	.000	0.	00	.000	0.000.0
	Re	~	0	0.	•	•	~	æ	0.	•	0.0000	9	٥.	0	9	•	0.	•	•	•	•	0.0000	•	0.0000	00.	0.	٥.	0.000	00.	00	0.0000
	003-	200	95.2	5.2	95.2	95	.200	0.	200	2.	•	~	.2	?	.2	.2	.2	0	7	M	$\sim$	~	S	7.5	2	3		•		15.200	.20
	003-	00	6. 7	6.67	24.8	0	74.8	47.8	787.32	8.66	612.36	54.	37.4	6 6 7	62.4	6.72	7.48	27,000	7.48	6.72	62.4	6 5	37.4	8.4	12.3		87.3	6.72	6.67	524.88	99.3
	7	0	0	0	0	0	0	0	-	-	-	0	_	0	-	-	-	0	0	0	0	0	0	0	0	0	0	0	0	0	Ç
																														0	
0																				6	C	_	~	~	7	S	9	7	<sub>∞</sub>	0 6	0
M	7										_	_	_	-	_	_	_	~	_	_	~	2	~	2	2	~	~	~	2	2	M

Truss-arch with pin-pin arch supports - page 2

\$1N .739 .000 .000 .000	000		262	26 41 53 62 00
674 1.000 1.000 1.000	000		284 84 99 99	96 91 91 91 92 93 94
Length 259.76 174.96 174.96 174.96	7 • 4 8 4 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9	87.480 87.480 87.480 87.480 87.480	7.16 03.7 0.13 0.69 7.84	0.69 6.13 6.13 7.16 4.71
Inertia 25.660 25.660 25.660 25.660	0000E-0	10000E 10000E 10000E 10000E 10000E		58.0 58.0 58.0 58.0
x-Area 7.0200 7.0200 7.0200 7.0200	06.	1.9000 1.9000 1.9000	22.22.2	2.12.12.12.12.12.12.12.12.12.12.12.12.12
0 N 4 M N X	. ø。	6 1 2 3 3 3 3 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4	- L B O O L V	4 2 2 2 2 1
Z 0 E - N M 7 N		, 60 1 1 2 2 4 2 4 2 4 2 4 2 4 2 4 2 4 2 4 2		NW4W9

A TOTAL CONTRACTOR IN THE CONTRACTOR IN THE PROPERTY OF THE PR

Truss-arch with pin-pin arch supports - page 3

1	1																											
	1,000	1.000	1.000	1.000	1.000	1,000	1.000	1,000	. 1. 000	1.000	1.000	1.000	739	739	.739	.739	1.000	1.000	•									
	000	000	000	000	000	000	000	000	000	000	000	000	.674	<b>929</b> °	.674	.674	000	000	000	000								
	8.53	1.47	140.40	52.3	7.67	2.3	52.3	7.67	40.4	8.53	1.47	4.71	59.7	2.65	59.7	59.7	2.00	2.00	2.00	2.00								
	0-3000	0-30000	0	7.2900	0000E-0	0	290	06	0000E-0	-3000	0-300C	0-300C	000E-0	000E-0	0-300C	000E-0	P	290	0	000		tLoa	000000		0.000	000	000	
	4.1	_		•	•	•	•	•	•	•	_	•	•	•	•	•	4.4100	•	•	•		ertlo	32000		43	8.910	.590	
	27 19	6	14 20	8 2	_	2 2	9 2	~	0 2	0 2	S	~	_	<b>—</b>			~	~	~	M		٦	0		•	0.000	000	
			62														43		4.5		NL J		10		12	28		

Truss-arch with pin-pin arch supports - page 4

```
-.21153E-04
                                -.29298E-03
                                           --21447E-03
                                                   .44524E-03
                                                            .16400E-03
                                                                     .19978E-04
                                                                              .11160E-02
                                                                                                                  -03
                                                                                                                                   -03
                                                                                                                                                                     .56860E-03
                                                                                                                                                                               .31486E-03
                                                                                                                                                                                        -.41326E-03
                                                                                                                                                                                               -.68273E-03
                                                                                                                                                                                                        -. 54267E-03
                                                                                                                                                                                                                 .54663E-04
                                                                                                                                                                                                                          .91394E-03
                                                                                                                                                                                                                                  .10340E-02
                                                                                                                                                                                                                                           .22947E-03
                                                                                                                                                                                                                                                    -.79949E-03
                                                                                                                                                                                                                                                             . 22899E-03
                                                                                                                                                                                                                                                                      .15067E-03
                                                                                                                                                                                                                                                                               -.53260E-03
                                                                                                                                                                                                                                                                                        -.44548E-03
                Rotationat
                                                                                                                                  .15438E
                                                                                                                 -. 54033E
                                                                                       000000
                                                                                                        0.0000
                                                                                                                         000000
                                                                                                                                            0.0000
                                                                                               000000
                                                                                                                                                    0.0000
                                                                                                                                                             000000
                                          -.84154E-01
                                                                                                                                                                               .28513E-01
                                                                                                                                                                                                                                                                              -.67174E-01
                                 -.26796E-01
                                                  -.67949E-01
                                                           -.17199E-01
                                                                                      .60391E-01
                                                                                               .87061E-01
                                                                                                        .25725E-01
                                                                                                                 -.66808E-01
                                                                                                                                   -.86000E-01
                                                                                                                                           -.36097E-01
                                                                                                                                                    .23984E-01
                                                                                                                                                                                        .23984E-01
                                                                                                                                                                                                -.31109E-01
                                                                                                                                                                                                                          -.67437E-01
                                                                                                                                                                                                                                  .26622E-01
                                                                                                                                                                                                                                           .87061E-01
                                                                                                                                                                                                                                                    .60391E-01
                                                                                                                                                                                                                                                             -23984E-01
                                                                                                                                                                                                                                                                      .87002E-01
                                                                                                                                                                                                                                                                                        .87061E-01
                                                                                                                                                             .28513E-01
                                                                                                                                                                                                        -.84638E-0
                Vertical
                                                                    0.000.0
                                                                              0.000.0
                                                                                                                         -.12188
                                                                                                                                                                                                                 -.11352
                                                                                                                                                                      0.0000
        Joint Displacements
                                 .14861E-01
                                                   -.17066E-02
                                                                                               .43915E-02
                                                                                                        .65872E-02
                                                                                                               .87829E-02
                                                                                                                         47551E-02
                                                                                                                                  72734E-03
                                                                                                                                                                                                .21059E-03
                                          .59868E-02
                                                            -.82224E-02
                                                                                      .21957E-02
                                                                                                                                            .54550E-03
                                                                                                                                                    .36366E-03
                                                                                                                                                                                                                                                             .10858E-02
                                                                                                                                                                                                                                                                      .11104E-02
                                                                                                                                                                                                                                                                              .15236E-01
                                                                                                                                                             .18182E-03
                                                                                                                                                                             -.24151E-01
                                                                                                                                                                                        -.23226E-01
                                                                                                                                                                                                        .13536E-01
                                                                                                                                                                                                                 .14942E-01
                                                                                                                                                                                                                          .17927E-01
                                                                                                                                                                                                                                   .42288E-01
                                                                                                                                                                                                                                           .68227E-01
                                                                                                                                                                                                                                                   .49332E-01
                                                                                                                                                                                                                                                                                        .71925E-02
                 Horizontal
Uniform
                         000000
                                                                      000000
                                                                              00000.0
                                                                                                                                                                      000000
```

## Truss-arch with pin-pin arch supports - page 5

K-Shear .62019E-02 -1.6111 22365E-01 2.3020 68707E-02 3.5037 43911E-0285331	32850E-0214659E-0 32945E-05 .14479E-0 14342E-05 .62731E-0 32983E-0514427E-0	.62469E-052547 .42325E-052036 .22926E-05 .9498 .30466E-05 .1385	-06 .10654E-0 -0568517E-0 -50.905 -01 -57.713 -01 9.5842 -01 9.5842 97.536 53.889 -39.550 -89.997	.822972758 .69634E-051345 .15719E-059134 .27221E-06 .1639
K-Axial -7.9427 -10.681 -9.2606 -7.8430	5.816 1.430 1.430	. 4307 . 9366 . 9366 11848	-11848 -5.7962 -5.8332 -5.7841 -5.1202 -5.0776 -5.0300 -5.3163 -5.5565	5.5230 .16026E-04 .46570E-04
J-Noment .69827E-04 1.6110 -2.3016 1.6216	.85345 .14342E-0 .62731E-0	2917 1666 1055 1279	999	50 768 781 504
J-Shear 62019E-02 .22365E-01 .68707E-02 .43911E-02	32850E-0 32945E-0 14342E-0 32983E-0	6246 4232 2292 3046 3230	.24358E-0 .15830E-0 .65974 .65608E-0 .74930 .52244E-0 1.0224 .49689 1.0981 .52474	8229 6963 1571 2722
J-Axial 7-9427 10.681 9.2606 7.8430	.816 .430 .430	.430 .936 .936 1184	11848 5.7962 5.8332 5.7841 5.0776 5.0300 5.3163 5.5565	.523 1602 4657 1665
TEU Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z	v 0 r &		14 115 117 118 119 22 22 24	

ALTERNATION OF SECURITION OF SECURITION OF SECURITION OF SECURITION OF SECURITION OF SECURITION OF SECURITIONS

Truss-arch with pin-pin arch supports - page 6

55 3 - 5 - 5 - 5 - 5 - 5 - 5 - 5 -	5523 6659 6659 6659 6659 71956 2000 2001 1096 2571 8242 56936-05 5452 5452 5452 1314	10293E-01 30629E-04 10269 10269 10269 27497E-05 27497E-05 1783E-04 22959E-06 19484E-06 15719E-05 15719E-05 15719E-05 15719E-05 15719E-05 15719E-05 15719E-05	45938E-03 45933E-03 2821 2837 76789E-04 12361E-03 31707E-03 3440E-04 35626E-04 55676E-03 25676E-03 25676E-03 25676E-03 25676E-03	1.5748 2.4300 15523 -1.6659 .32000 26007E- 34195E- 34195E- 23085E- 24096 2571 95693E- 75136 13499E- 13499E- 13499E-	.30629E-04 10484E-06 23562E-01 .10269 14086E-05 .02 .27497E-05 .0511783E-04 65386E-07 .22959E-06 13129E-06 .19484E-06 .17299E-01 23556E-01	-1.8556 -38816E-03 -99836E-05 3.8714 -5.1253 -12098E-03 -12790E-03 -12790E-03 -12790E-03 -13789E-04 -33583E-04 -33583E-04 -17171E-04 -17171E-04 -17171E-04 -17171E-04
2.1.1.2.2.2.2.2.2.2.2.2.2.2.2.2.2.2.2.2	3216 172 172 858 300 2299 2299	.31859E- .97873E- .62551E- .46795E- .17339E- .75483E- -17360E- -32878E-	02 - 318 03 - 625 03 - 625 05 - 173 06 - 754 05 - 173 05 - 173	59E-02 73E-03 51E-03 95E-03 39E-05 60E-05 78E-05	2.3020 3.5037 1.6216 .85345 .14479E-03 .62731E-04 .14427E-03	

Truss-arch with pin-pin arch supports - page 7

0443E-06 .10557E-0	16035E-05 .13855E-0	0-2001	17004E-05 .14132E-0	17004E-05 .14132E-0 12820E-06 .10654E-0 83318E-06 .69968E-0	17004E-05 .1413 12820E-06 .1065 83318E-06 .6996 54165E-01 50.90	17004E-05 .14132E-0 12820E-06 .10654E-0 83318E-06 .69968E-0 54165E-01 50.905 53865E-02 57.713	17004E-05 .14132E-0 12820E-06 .10654E-0 83318E-06 .69968E-0 54165E-01 50.905 53865E-02 57.713 61519E-01 57.713	170046-05 .141326-0 128206-06 .106546-0 833186-06 .699686-0 541656-01 50.905 538656-02 57.713 615196-01 57.713	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .61519e-01 57.713 .42893e-02 14.323	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .61519e-01 57.713 .42893e-01 57.713	170046-05 .141326-0 128206-06 .106546-0 833186-06 .699686-0 541656-01 50.905 538656-02 57.713 615196-01 57.713 428936-02 14.323 839386-01 97.536 407956-01 97.537	.170046-05 .141326-0 .128206-06 .106546-0 .833186-06 .69968E-0 .541656-01 .69968E-0 .538656-02 .713 .615196-01 .57.713 .428936-02 .713 .428936-01 .57.713 .407956-01 .97.536 .407956-01 .97.537 .407956-01 .89.997	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .42893e-02 14.323 .83938e-01 97.536 .40795e-01 60.045 .43082e-01 89.997	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .61519e-01 57.713 .42893e-02 14.323 .83938e-01 97.536 .40795e-01 97.537 .90160e-01 60.045 .43082e-01 89.997 .20964e-01 89.997	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .61519e-01 57.713 .42893e-02 14.323 .83938e-01 97.536 .40795e-01 97.536 .40795e-01 89.997 .20964e-01 89.997 .67567e-01 63.500	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .42893e-01 57.713 .42893e-01 57.713 .40795e-01 97.536 .40795e-01 97.537 .90160e-01 60.045 .43082e-01 89.997 .20964e-01 89.997 .41697e-05 .17681e-0	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .42893e-01 57.713 .42893e-01 57.713 .40795e-01 97.536 .40795e-01 97.537 .50964e-01 89.997 .50964e-01 63.500 .41697e-05 .17681e-0 .35644e-06 .91344e-0	.170046-05 .141326-0 .128206-06 .106546-0 .833186-06 .69968E-0 .541656-01 50.905 .428936-01 57.713 .428936-01 57.713 .407956-01 97.536 .407956-01 97.537 .509646-01 60.045 .209646-01 63.500 .416976-05 .15816-0 .356446-06 .913446-0 .375926-06 .586596-0	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 .50.905 .53865e-02 .57.713 .42893e-01 .57.713 .42893e-01 .57.713 .40795e-01 .97.536 .40795e-01 .97.537 .90160e-01 .60.045 .43082e-01 .89.997 .20964e-01 .89.997 .27521e-05 .16394e-0 .37592e-06 .58659e-0	.17004e-05 .14132e-0 .12820e-06 .10654e-0 .83318e-06 .69968e-0 .54165e-01 .69968e-0 .54856-02 .713 .42893e-02 .713 .42893e-01 .57.713 .40795e-01 .97.536 .40795e-01 .89.997 .20964e-01 .89.997 .20964e-01 .89.997 .27521e-05 .91344e-0 .37592e-06 .58659e-0 .37592e-06 .58659e-0 .37643e-02 .18556	.17004e-05 .14132e-0 .12820e-06 .69968e-0 .83318e-06 .69968e-0 .54165e-01 .69968e-0 .53865e-02 .713 .42893e-02 .713 .42893e-02 .713 .42893e-01 .97.536 .40795e-01 .97.537 .90160e-01 .60.045 .43082e-01 .89.997 .20964e-01 .89.997 .27567e-01 .17681e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0	.17004e-05 .14132e-0 .12820e-06 .69968e-0 .83318e-06 .69968e-0 .54165e-01 50.905 .53865e-02 57.713 .61519e-01 57.713 .42893e-02 14.323 .83938e-01 97.536 .40795e-01 97.537 .90160e-01 89.997 .20964e-01 89.997 .20964e-01 89.997 .21697e-05 .17681e-0 .37592e-06 .91344e-0	.17004e-05 .14132e-0 .12820e-06 .69968e-0 .83318e-06 .69968e-0 .54165e-01 .69968e-0 .54165e-01 .57.713 .42893e-02 .77.33 .42893e-01 .57.713 .40795e-01 .97.536 .40795e-01 .97.537 .50964e-01 .89.997 .50964e-01 .89.997 .51697e-05 .16394e-0 .57567e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37592e-06 .91344e-0 .37643e-02 .16394e-0 .37643e-02 .16394e-0 .37643e-02 .16394e-0 .37643e-02 .16394e-0 .37643e-02 .16394e-0 .37643e-02 .16394e-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 50.905 .541656-02 57.713 .428936-02 14.323 .428936-01 97.536 .407956-01 97.537 .901606-01 60.045 .430826-01 89.997 .575676-01 63.500 .416976-05 .913446-0 .272216-02 .913446-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-00 .91346-0 .375926-00 .91346-0 .375926-00 .91346-0 .375926-00 .91346-0 .375926-00 .912336-0 .375926-00 .912336-0 .375926-00 .912336-0 .375926-00 .912336-0 .375926-00 .912336-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 50.905 .541656-01 57.713 .428936-02 57.713 .428936-01 57.713 .428936-01 57.536 .407956-01 97.536 .407956-01 60.045 .430826-01 69.997 .5756-01 63.500 .416976-01 63.500 .416976-05 .913446-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .376436-02 .163946-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .375926-06 .91346-0 .459336-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 .69968E-0 .541656-01 .50.905 .538656-02 .57.713 .428936-01 .57.713 .428936-01 .57.536 .407956-01 .97.537 .901606-01 .60.045 .430826-01 .89.997 .20964E-01 .89.997 .21697E-05 .16394E-0 .37592E-06 .91344E-0 .37592E-06 .91349E-0 .37592E-06 .91349E-0 .27497E-01 .12098E-0 .27497E-01 .12790E-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 .69968E-0 .541656-01 .50.905 .538656-02 .57.713 .428936-01 .57.713 .428936-01 .57.713 .407956-01 .97.537 .901606-01 .60.045 .430826-01 .89.997 .20964E-01 .89.997 .21697E-05 .16394E-0 .375926-06 .91344E-0 .27631E-01 .12098E-0 .27497E-01 .12790E-0 .27497E-01 .12790E-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 .69968E-0 .541656-01 .69968E-0 .538656-02 .713 .428936-01 .57.713 .428936-01 .57.713 .407956-01 .97.536 .407956-01 .97.537 .20964E-01 .89.997 .20964E-01 .89.997 .27521E-02 .91344E-0 .37592E-06 .91349E-0 .37592E-06 .91349E-0 .37592E-06 .91349E-0 .37592E-06 .91349E-0 .37592E-06 .91349E-0 .37592E-06 .91349E-0 .37592E-06 .913796E-0 .27497E-01 .12790E-0 .27497E-01 .12790E-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 .69968E-0 .541656-01 .69968E-0 .538656-02 .713 .42893E-01 .57.713 .42893E-01 .97.536 .40795E-01 .97.537 .90160E-01 .97.537 .40795E-01 .97.537 .41697E-05 .91344E-0 .41697E-05 .91344E-0 .41697E-06 .91344E-0 .41697E-01 .91344E-0 .41697E-01 .91344E-0 .41697E-01 .91344E-0 .41697E-01 .91344E-0 .41697E-01 .913789E-0 .41697E-01 .913789E-0 .41697E-01 .913789E-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541656-01 .69968E-0 .541656-01 .69968E-0 .541656-02 .713 .42893E-02 .42893E-03 .40795E-01 .97.536 .43082E-01 .97.537 .90160E-01 .97.537 .90160E-01 .97.537 .41697E-05 .91344E-0 .27221E-02 .91344E-0 .37592E-06 .91344E-0 .37592E-06 .91346E-0 .37592E-06 .91346E-0 .37592E-06 .91346E-0 .37592E-06 .91346E-0 .37592E-06 .91346E-0 .37592E-06 .91346E-0 .37592E-06 .16398E-0 .3759E-07 .99836E-0 .3759E-01 .12098E-0 .27497E-01 .12790E-0 .33193E-07 .33583E-0	.170046-05 .141326-0 .128206-06 .69968E-0 .541658-01 .69968E-0 .541658-01 .69968E-0 .541658-02 .713 .428938-02 .713 .428938-02 .713 .428938-01 .97.536 .407958-01 .97.537 .901608-01 .89.997 .430828-01 .89.997 .509648-01 .89.997 .509648-00 .913448-0 .375928-06 .913448-0 .375928-06 .913448-0 .375928-06 .913448-0 .375928-06 .913448-0 .375928-06 .913448-0 .37598-00 .120988-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45938-0 .45978-0 .45938-0 .45938-0 .4596-0 .45988-0 .45988-0 .45988-0 .45478-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0 .45988-0	.170046-05 .141326-0 .128206-06 .69968E-0 .54165E-01 .69968E-0 .54165E-01 .69968E-0 .54165E-01 .50.905 .53865E-02 .57.713 .42893E-02 .57.713 .42893E-01 .97.536 .40795E-01 .97.537 .90160E-01 .60.045 .43082E-01 .97.537 .40795E-01 .97.537 .41697E-05 .91344E-0 .27567E-06 .58659E-0 .37592E-06 .58659E-0 .37592E-06 .58659E-0 .37592E-06 .58659E-0 .37592E-06 .58659E-0 .37592E-06 .58659E-0 .37592E-07 .58659E-0 .37592E-06 .58659E-0 .37592E-07 .38659E-0 .37592E-06 .58659E-0 .37592E-06 .58659E-0 .37592E-07 .33789E-0 .37596-07 .33789E-0 .33193E-07 .33740E-0	.170046-05 .128206-06 .833186-06 .541656-01 .541656-01 .538656-02 .538656-02 .428936-01 .428936-01 .428936-01 .407956-01 .407956-01 .407956-01 .407956-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .416976-01 .41697
.17004E-0512820E-06 -	12820E-0	1 20202	833186-0	.54165E-0	53865E-0	.61519E-0	42893E-0	83938E-01	.40795E-01	90160E-01	.43082E-0	.20964E-01	67567E-01	.41697E-05	35644E-0	.27221E-02	37592E-06	.37643E-02	10210E-04	.62777E-07	78540E-02	34231E-0	84347E-0	60559E-06	27497E-0	70555E-0	33193E-0	13748E-0	78617E-0	97420E-0	35645E-0	37664E-0	78520E-0
0 1016	2359E-0	22596-0	623546-01	7588	4789	748	203	4168	4129	4364	4562	818	4534	95962E-	10560E-0	6.655	.065	4654	549	.455	5174	.55529	1916	5897	.195	.1382	.954	1.263	1.3516	.912	.2169	.504	0150
- :	75	2 2	- t	16				20																									

(4) Load Position 2 - Upstream truss-arch with fixed-fixed arch supports

Rot Load 0.0000	0.0000 0.0000 0.0000 0.0000 0.0000 153236-04 153866-03 153606-03 .303496-03 .971356-05 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000 0.0000	
VertLoad R	-2.4300 -8.9100 -2.5900 -2.5900 23276E-01 71994E-01 71994E-01 71994E-01 56507E-01 56507E-01 56506E-01 56406E-01 56406E-01 56406E-01 56406E-01 27856E-01 10519 75006E-01 75006E-01	)
0.0000 0.0000	0.0000 0.0000 0.0000 0.0000 0.0000 12705E-01 -12705E-01 -12705E-01 -12705E-02 -19069E-02 0.0000 0.0000 1884E-02 0.0000 1884E-02 -1969E-02 -19691E-03 -19697E-03 -19697E-03	
N	N	

Truss-arch with fixed-fixed arch supports - page 2

	K-Moment -1.4434 2.3697 1.6529 87360	57854E-04 .56593E-04 .8441E-04 86310E-03 17521E-03 .17521E-03 .13357E-03 .11185E-03
·	K-Shear .55567E-02 -21794E-01 .40953E-02 .26253E-02	33633E-02 12862E-05 19305E-05 .19733E-05 .52908E-05 20116E-05 29241E-05 25572E-05
	K-Axial -7.0105 -9.4259 -8.1622 -6.4898	-4.8175 -1.2278 -1.2278 -1.2278 3.2984 3.2984 3.2984 3.2984 3.2984
30416E-03 22328E-03 59968E-03 49186E-03 4917E-04 79603E-03 79744E-03 55489E-04 60763E-03 16708E-03 16708E-03	J-Moment .32457E-04 1.4434 -2.3694 .41428	.87371 .55927E-04 .84441E-04 86310E-04 24654E-03 14497E-03 .93653E-04 .12223E-03 .11185E-03
.12941E-01 22868E-01 72428E-01 55987E-01 23596E-01 23596E-01 23494E-01 75919E-01 56696E-01 56696E-01 56696E-01 56696E-01 56696E-01	J-Shear 55567E-02 -21794E-01 40953E-02 26253E-02	.33633E-02 .12862E-05 .19305E-05 19733E-05 52908E-05 36600E-05 .20116E-05 .29241E-05 .25572E-05
12327E-01 19261E-01 .96228E-02 .10178E-01 .12240E-01 .32078E-01 .46156E-01 .20656E-01 66104E-03 11811E-02	er-End Act J-Axial 7.0105 9.4259 8.1622 6.4898	4.8175 1.2278 1.2278 1.2278 1.2278 -3.2984 -12834 -12834
		2 4 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5

Truss-arch with fixed-fixed arch supports -.28491E-03 .81687E-05 -.61660E-04 .20164E-04 -.53719E-04 .92287E-04 .68871E-04 -- 98026E-04 .59231E-05 .13299E-04 -.27240E-04 .13982E-04 -.13345E-04 .35204E-04 -.55345E-04 -.31123E-04 -61.895 17.115 46.089 -16.787 -54.860 -82.479 121.79 -1.7492 3.2927 -2.0672 -.12758 .23996 1.2874 .11182 82.751 -.95360E-07 .10941E-05 .10646E-01 .23244E-04 .58270E-06 .23048E-05 -.46641E-06 .15592E-06 -.81699E-07 -.10719E-05 .22958E-05 -.64683E-07 .18419E-06 .10942E-05 -.20040E-01 -.14031E-05 -. 20883E-05 .10651E-01 -. 20034E-01 -. 14033E-05 -.13197 .43470 .28728 -.17452 -.76710 .41737 -1.5770 1.2125 -. 79591 -.65721 90--04 -.35606E-05 -.16898E-03 -.24298E-02 -.19628E-05 -.42626E-04 -.14094E-02 .50841E -. 72645E 6.9779 -7.7869 6906-9-.7800 1.4126 -1.6920 .32000 -7.0956 -6.8752 -7.5070 -7.7372 -7.7030 -7.5819 2.4300 .41874 -7.7704 2.0624 -1.8762 2.2871 -6.8475 4.8141 -03 -. 35204E-04 .55346E-04 -.11197E-03 .35029E-05 44325E-03 .22499E-04 .59081E-05 .87457E-04 -.20605E-04 -.27157E-04 -.48334E-04 -.22854E-03 -.71936E-04 ..58208E-04 .10739E-04 .72185E-04 -. 28092E-04 -.35826E +82.752 -.11189 .12755 .16.787 61.895 -1.2876 -15.367 54.860 82.479 -.24002 5.7188 -55.101 -.10941E-05 .46641E-06 -.58270E-06 -.18419E-06 -.22958E-05 .64683E-07 .95360E-07 -.15592E-06 -. 10942E-05 -.23048E-05 -. 23244E-04 .81699E-07 .14031E-05 -. 10646E-01 .10719E-05 .20383E-05 . 20040E-01 -.10651E-01 20034E-01 .14033E-05 -.43470 .76710 -.41737 -1.2125 -.28728 1.5770 .13197 .65721 .17452 .79591 .42626E-04 -.50841E-06 .35606E-05 .24293E-02 .14094E-02 .16898E-03 .19628E-05 .7264 SE-04 .7869 .7030 .0956 6906.9 6.8752 .5070 .7372 .5819 -1.7800 -2.4300 -6.9779 .7704 -2.0624 -1.4126 -- 41874 1.6920 -.32000 1.8762 6.8475 -4.8141 -2.2871

36

37

39

40

38

24

23

59

TANKS TO SERVICE TO SE

Truss-arch with fixed-fixed arch supports - page 5

28 -14.09446641E-0246641E-02224999E 29  1.065934892E-0634892E-0635486E-0235486E-0235486E-0235486E-0235486E-0235486E-0235486E-0235486E-0235826E 31  .4708748922E-0748922E-0781687E 32  1.455148922E-0748922E-0781687E 33  .1395866800E-0243990E-0143990E-0143990E-0143990E-015539964186E-0654186E-0692287E 35 1916264186E-0631816E-0692287E 36 38318E-0431816E-0652958E-0111197E 37 22958E-0122958E-0111029E-0587457E 39 32341E-0732341E-0712505E-0713982E 41  1.369557102E-0777960E-0713982E 42 2282557102E-0757102E-071575857102E-02557102E-072282557102E-07228354E2282524811E-0624811E-0625895625399626779E-0225895E-0226779E-0225895E-0325879E-0325879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225879E-0225					
9       1.0659      34892E-06       .34892E-06         1       .47087      35486E-02       .35486E-02         1       .47087      77481E-05       .77481E-05         1       .47087      48922E-07      48922E-07         2       .13958       .66800E-02      64800E-02         4      56399       .43990E-01      43990E-01         5       .19162       .64186E-06      64186E-06         6      38318E-04       .31816E-06      54186E-06         7       -24.298      22958E-01       .22958E-01         8      1753E-05      15505E-05         9       .32341E-07      35341E-07         1       .3695      37960E-07         1       .3695      37960E-07         1       .57102E-07      57102E-07         2       .4811E-06      57102E-07         2       .24811E-06      57359E-02        77960E-07      57379      66779E-02        75379      6779E-02      5579E-02        75379      31821E-06      31821E-06	28	14.09	.46641E-02	46641E-0	
0 .6874735486E-02 .35486E-02 .77481E-05 .48922E-0748922E-07 .68800E-0266800E-02 .43990E-0143990E-01 .43990E-01 .43990E-01 .73990E-01 .73990E-01 .73990E-01 .22958E-01 .22958E-05 .24811E-06 .24811E-0	59	55	-34892E-	34892E-0	.53719E-04
1 .4708777481E-05 .77481E-05 .77481E-05 .48922E-07 .48922E-07 .48922E-07 .48922E-07 .48922E-07 .48922E-07 .48922E-07 .43990E-01 .43990E-01 .43990E-01 .43990E-01 .43990E-01 .43990E-01 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .12505E-05 .11753E-05 .12505E-05 .11753E-05 .11029E-06 .11029E-07 .77960E-07 .	30	7	-35486E-	35486E-0	
2       1.4551       .48922E-07      48922E-07         3       .13958       .66800E-02      66800E-02         4       .990E-01      43990E-01         5       .19162       .64186E-06      54186E-06         6       .38318E-04       .31816E-06      31816E-06         7       -22958E-01       .22958E-01         8      17505E-05      12505E-05         9       3.4889      32341E-07         -1.1234      11029E-06       .11029E-07         1       1.3695       .57102E-07         2       2.4071      77960E-07         11529E-06      24811E-06       .24811E-06         -2.2825      35502E-02      66779E-02         -77379      31821E-06      31821E-06	31	9	-77481E-	77481E-0	-0
3 .1395866800E-0266800E-0243990E-0143990E-0143990E-0143990E-0143990E-0143990E-0125399E-0122958E-0631816E-0631816E-0631816E-0631816E-0631836E-0122958E-0122958E-0122958E-0122958E-0122958E-0132341E-0732341E-0732341E-0732341E-0732341E-0732341E-0637960E-0777960E-0777960E-0777960E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-0757102E-	32	5	.48922E-07		.81687E-05
456399 .43990E-0143990E-01 5 .19162 .64186E-0664186E-06 638318E-04 .31816E-0631816E-06 7 -24.29822958E-01 .22958E-01 811753E-05 .12505E-0512505E-05 9 3.4889 .32341E-0732341E-07 1 1.3695 .57102E-07 .77960E-07 2 2.407177960E-07 .77960E-07 3 .11529E-0624811E-06 .24811E-06 572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	33	35	66800E-02		
5 .19162 .64186E-0664186E-06 38318E-04 .31816E-0631816E-06 -24.298122958E-01 .22958E-01 811753E-05 .12505E-0512505E-05 9 3.4889 .32341E-0732341E-07 -1.123411029E-06 .11029E-06 1 1.3695 .57102E-07 .77960E-07 2 2.407124811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0631821E-06	34	.5639	.43990E-01	.43990E-0	
638318E-04 .31816E-0631816E-06 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .22958E-01 .324689 .32341E-0732341E-07 .11029E-06 .11029E-07 .32341E-06 .11029E-07 .37960E-07 .77960E-07 .77960E-07 .77960E-07 .77960E-07 .35502E-02 .35502E-02 .35502E-02 .35502E-02 .35502E-0616473E-04 .31821E-0631821E-06	25	16	.64186E-06	64186E-0	. 1
7 -24.29822958E-01 .22958E-01 811753E-05 .12505E-0512505E-05 9 3.4889 .32341E-0732341E-07 1.123411029E-06 .11029E-06 1 1.3695 .57102E-0757102E-07 2 2.407177960E-07 .77960E-07 3 .11529E-0624811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0631821E-06	98	.38318E	.31816E-06	.31816E-0	
811753E-05 .12505E-0512505E-05 3.4889 .32341E-0732341E-07 0 -1.1234 0.11029E-06 0.11029E-06 0.11029E-06 0.11029E-07 0.24071 0.27960E-07 0.24811E-06 0.24811E-06 0.25379E-05 0.25379E-05 0.25379E-05 0.25379E-05 0.31821E-06 0.318	25	24.29	22958E-01	22958E-0	1
9 3.4889 .32341E-0732341E-07 1 1.3695 .57102E-06 .11029E-06 2 2.407177960E-07 .77960E-07 3 .11529E-0624811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	88	-11753E-	.12505E-05	.12505E-0	
0 -1.123411029E-06 .11029E-06 1 1.3695 .57102E-0757102E-07 2 2.407177960E-07 .77960E-07 3 .11529E-0624811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	65	389	.32341E-07	.32341E-0	1
1 1.3695 .57102E-0757102E-07 2 2.407177960E-07 .77960E-07 3 .11529E-0624811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	0	1.123	-11029E-	1029E-0	1
2 2.407177960E-07 .77960E-07 3 .11529E-0624811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	-	1.3695	.57102E-07	.57102E-0	1
3 .11529E-0624811E-06 .24811E-06 4 -2.282535502E-02 .35502E-02 572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	2:	2.4071	.77960E-0	77960E-0	1
4 -2.282535502E-02 .35502E-02 572379 .66779E-0266779E-02 616473E-04 .31821E-06	m	529E-	.24811E-0	24811E-0	.1.
572379 .66779E-0266779E-02 616473E-04 .31821E-0631821E-06	_	2.282	.35502E-0	35502E-0	.12758
616473E-04 .31821E-0631821E-06		.7237	66779E-0	0-36278	.23996
	_	.16473	31821E-0	.31821E-0	.72185E-04

Truss-arch with fixed-fixed arch supports - page 4

Maximum Moment 1.4434	2.3697 2.3694 .87360 .87350 .87371 .56593E-04 .86310E-04 .24654E-03 .17521E-03 .17521E-03 .17521E-03 .17521E-03 .17521E-03 .17521E-04 .24654E-03 .17521E-04 .24654E-03 .17521E-04 .77936E-04
Member K-Shear . 79155E-03	- 31046E-02 - 58338E-03 - 47911E-03 - 67697E-06 - 10161E-05 - 10386E-05 - 70581E-06 - 15390E-05 - 15390E-05 - 15390E-05 - 15390E-01 - 15390E-01 - 15390E-01 - 15396E-01 - 53958E-01 - 53958E-01 - 53958E-01 - 65345E-01 - 65345E-01
and Moment on J-Shear 79155E-03	.31046E-02 -37397E-03 -47911E-03 -67697E-06 -10161E-05 -10386E-05 -12842E-05 -12842E-05 -13459E-05 -13459E-01 -35689E-01 -35689E-01 -34267E-01 -34267E-01 -34267E-01
Case Stresses Axial 99865	-1.3427 -1.1627 64622 64622 64622 64622 64622 64622 64622 64622 64622 64622 64622 64622 64622 64622 67548E-01 67548E-01 67548E-01 67548E-01 67548E-01 67548E-01 67548E-01 67546 67546 63243 63243 63249 63249
MEN TO TE	25

FILMED

ASS

DTIC